

Makita	BUH650	Cordless Hedge Trimmer	IA	-	-	60745-2-15			92,4	-	Guaranteed-94-dB	2000/14/EC
Makita	BUX360	Cordless Cultivator	IA	2,5	1,5	EN709		≤	70	2,5	no-load	EN709
Makita	BUX360	Cordless Cultivator	IA	-	-	-			79	-	Guaranteed-81-dB	2000/14/EC
Makita	BUM166	Cordless Grass Shear	IA/IA	2,5	1,5	IEC60335-2-94			77	2,5	no-load	IEC60335-2-94
Makita	BUM168	Cordless Grass Shear	IA/IA	2,5	1,5	IEC60335-2-94			78	-	no-load	IEC60335-2-94
Makita	BUN490	Cordless Pole Hedge Trimmer	IA	5,5/-2,0	1,5/-1,5	ISO10517			82,9	93,2	2/-2,2	Uncertainty: K _{PA} /K _{WA}
Makita	BUN490	Cordless Pole Hedge Trimmer	IA	-	-	-			93,2	-	-	Guaranteed-95-dB
Makita	BUR142U	Cordless String Trimmer	IA	2,5	1,5	EN786			78	89	1,0	no-load
Makita	BUR142U	Cordless String Trimmer	IA	-	-	-			89	-	-	Guaranteed-90-dB
Makita	BUR143U	Cordless String Trimmer	IA	2,5	1,5	EN786			78	89	1,0	no-load
Makita	BUR143U	Cordless String Trimmer	IA	-	-	-			89	-	-	Guaranteed-90-dB
Makita	BUR181	Cordless String Trimmer	IA	2,5	1,5	EN786			82	88,5	2,5	no-load
Makita	BUR181	Cordless String Trimmer	IA	-	-	-			88,0	-	1,5	Guaranteed-91-dB
Makita	BUR182U	Cordless String Trimmer	IA	2,5	1,5	EN786			79	90	0,7	no-load
Makita	BUR182U	Cordless String Trimmer	IA	-	-	-			90	-	-	Guaranteed-90-dB
Makita	BUR183U	Cordless String Trimmer	IA	2,5	1,5	EN786			79	90	0,7	no-load
Makita	BUR183U	Cordless String Trimmer	IA	-	-	-			90	-	-	Guaranteed-90-dB
Makita	BUR360 (UR360D)	Cordless String Trimmer	IA	5,5	1,5	EN786			82	90	0,4	no-load
Makita	BUR360 (UR360D)	Cordless String Trimmer	IA	-	-	-			90	-	-	Guaranteed-91-dB
Makita	BUX360	Edger Attachment	IA	1,9/1,2	1,5/1,5	ISO11789			76,7	90,9	2,7/2,4	Uncertainty: K _{PA} /K _{WA}
Makita	BUX360	Edger Attachment	IA	-	-	-			90,9	-	-	Guaranteed-94-dB
Makita	BUX360	Brushcutter Attachment	IA	2,5	1,5	EN11806			80,1	93,5	2,5/2,5	Uncertainty: K _{PA} /K _{WA}
Makita	BUX360	Brushcutter Attachment	IA	-	-	-			93,1	-	-	Guaranteed-95-dB
Makita	BUX360	String Trimmer Attachment	IA	4,0	1,5	EN786			78,6	91,7	2,5/2,5	Uncertainty: K _{PA} /K _{WA}
Makita	BUX360	String Trimmer Attachment	IA	-	-	-			92,8	-	-	Guaranteed-95-dB
Makita	BUX360	Hedge Trimmer Attachment	IA	3,5/2,5	1,5/1,5	ISO10517			86	94,8	2,5/2,5	Uncertainty: K _{PA} /K _{WA}
Makita	BUX360	Hedge Trimmer Attachment	IA	-	-	-			94,6	-	-	Guaranteed-97-dB
Makita	BUX360	Hedge Trimmer Attachment	IA	3,0	2,0	ISO10517			81,8	97,3	3,0/3,0	Uncertainty: K _{PA} /K _{WA}
Makita	BUX360	Hedge Trimmer Attachment	IA	-	-	-			97,0	-	-	Guaranteed-100-dB
Makita	BUX360	Pole Hedge Trimmer Attachment	IA	5,5	1,5	ISO10517			83,5	92,8	2,3/2,6	Uncertainty: K _{PA} /K _{WA}
Makita	BUX360	Pole Hedge Trimmer Attachment	IA	-	-	-			92,8	-	-	Guaranteed-95-dB
Makita	BUX360	Pole Hedge Trimmer Attachment	IA	3,5	1,5	ISO10517			79,8	93,4	1,8/2,1	Uncertainty: K _{PA} /K _{WA}
Makita	BUX360	Pole Hedge Trimmer Attachment	IA	-	-	-			93,4	-	-	Guaranteed-95-dB
Makita	BUX360	Pole Hedge Trimmer Attachment	IA	3,5	1,5	ISO10517,EN60745			79,7	90,8	1,16/0,87	Uncertainty: K _{PA} /K _{WA}
Makita	BUX360	Pole Hedge Trimmer Attachment	IA	-	-	-			90,8	-	-	Guaranteed-92-dB
Makita	BUX360	Pole Hedge Trimmer Attachment	IA	3,5	1,5	ISO10517,EN60745			79,1	89,6	1,12/0,88	Uncertainty: K _{PA} /K _{WA}
Makita	BUX360	Pole Hedge Trimmer Attachment	IA	-	-	-			89,6	-	-	Guaranteed-91-dB
Makita	BUX360	Ground Trimmer Attachment	IA	5,0	1,5	ISO10517,EN60745			82,5	93,52	1,25/0,99	Uncertainty: K _{PA} /K _{WA}
Makita	BUX360	Ground Trimmer Attachment	IA	-	-	-			93,52	-	-	Guaranteed-95-dB
Makita	BUX360	Pole Saw Attachment	IA/IA/IA/IA	2,5	1,5	ISO11680-1			91,9	100,9	2,5/2,5	Uncertainty: K _{PA} /K _{WA}
Makita	BUX360	Pole Saw Attachment	IA/IA/IA/IA	2,5	2,0	ISO11680-1			88,8	102,9	2,5/2,5	Uncertainty: K _{PA} /K _{WA}
Makita	BUX360	Pole Saw Attachment	IA/IA/IA/IA	2,5	2,0	ISO11680-1			93,6	101,9	2,5/2,5	Uncertainty: K _{PA} /K _{WA}
Makita	BUX360	Pole Saw Attachment	IA/IA/IA/IA	2,5	2,0	ISO11680-1			90,3	104,4	2,5/2,5	Uncertainty: K _{PA} /K _{WA}
Makita	BUX360	Coffee Harvester Attachment	IA/IA/IA/IA	3,5/3,0	1,5/1,5	ISO10517			78,2	87,1	2,5/2,5	Uncertainty: K _{PA} /K _{WA}
Makita	BUX360	Coffee Harvester Attachment	IA/IA/IA/IA	2,5	2,0	ISO10517			81,9	96,2	2,5/2,5	Uncertainty: K _{PA} /K _{WA}
Makita	BUX360	Cultivator Attachment	IA/IA/IA/IA	2,5	1,5	EN709			78,8	88,3	2,5/2,5	Uncertainty: K _{PA} /K _{WA}
Makita	BUX360	Cultivator Attachment	IA/IA/IA/IA	2,5	1,5	EN709			85,6	97,0	1,0/2,0	Uncertainty: K _{PA} /K _{WA}
Makita	BV13-177	HUCK Rechargeable Battery tool	IA	1,3	1,5	EN62841-1		89	-	97	3	Installing lockbolt
Makita	BV13-177	HUCK Rechargeable Battery tool	IA	1,2	1,5	EN62841-1		79	-	-	3	No load
Makita	BV17-177	HUCK Rechargeable Battery tool	IA	0,5	1,5	EN62841-1		80	-	88	3	Installing lockbolt
Makita	BV17-177	HUCK Rechargeable Battery tool	IA	1,2	1,5	EN62841-1		79	-	-	3	No load
Makita	BV2200-118	HUCK Rechargeable Battery tool	IA	0,5	1,5	EN62841-1		72	-	-	3	Installing lockbolt
Makita	BV4500-118	HUCK Rechargeable Battery tool	IA	2,0	1,5	EN62841-1		80	-	88	3	Installing blind rivet
Makita	BVF104	Cordless Sprayer	IA/IA	2,5	1,5	60745-1, EN50580		≤	70	-	3	no-load
Makita	BVF154	Cordless Sprayer	IA/IA	2,5	1,5	60745-1, EN50580		≤	70	-	3	no-load
Makita	CA5000	Circular Saw	IA	2,5	1,5	EN62841-2-5		91	-	99	3	cutting-chipboard
Makita	CA5000	Circular Saw	IA	2,5	1,5	EN62841-2-5			-	-	-	-
Makita	CA5000	Circular Saw	IA	2,5	1,5	EN62841-2-5			-	-	-	-
Makita	CC300D	Cordless Cutter	IA	2,5	1,5	60745-2-22			83	94	3	concrete-cutting (depth=25.5mm)
Makita	CC301D	Cordless Cutter	IA	2,5	1,5	60745-2-22			84	95	3	concrete-cutting (depth=25.5mm)
Makita	CE001G	Cordless Power Cutter	IA	2,5	1,5	60745-2-22			109	120	3	-
Makita	CE001G	Cordless Power Cutter with Cart	IA	0,5	1,5	EN13862		-	101	-	3	Uncertainty: K _{PA}
Makita	CE001G	Cordless Power Cutter with Cart	IA	-	-	-		-	-	117,93	1,95	Guaranteed-120-dB
Makita	CE001G	Cordless Power Cutter with Cart	IA	-	-	-		-	-	117,93	1,95	Guaranteed-120-dB
Makita	CE001G	Cordless Power Cutter with Cart	IA	-	-	-		-	86	-	3	Uncertainty: K _{PA}
Makita	CE001G	Cordless Power Cutter with Cart	IA	-	-	-		-	-	99,24	0,85	Guaranteed-100-dB
Makita	CE002G	Cordless Power Cutter	IA	2,5	1,5	60745-2-22			106	117	3	-
Makita	CE003G	Cordless Power Cutter	IA	3,0	1,5	60745-2-22			105	116	3	-
Makita	CE004G	Cordless Power Cutter	IA	3,8	1,5	60745-2-22			99	110	3	-
Makita	CE090D	Cordless Power Cutter	IA	5,9/4,0	1,5	60745-2-22			71	103	114	3
Makita	CG100D	Cordless Caulking Gun	IA	0,3	1,5	EN62841-1			-	-	3	no-load
Makita	CL070D	Cordless Cleaner	IA	-	-	-			-	-	-	-
Makita	CL072D	Cordless Cleaner	IA	-	-	-			-	-	-	-
Makita	CL100D	Cordless Cleaner	IA	-	-	-			-	-	-	-
Makita	CL102D	Cordless Cleaner	IA	-	-	-			-	-	-	-
Makita	CP100D	Cordless Multi Cutter	IA	0,6	1,5	EN62841-1		71	-	-	3	no-load
Makita	CS002G(CS001G)	Cordless Metal Cutter	IA/IA	2,5	1,5	EN62841-2-5		105	-	113	3	cutting-sheet-aluminium
Makita	DA001G(DA002G)	Cordless Angle Drill	IA/IA	2,5	1,5	EN62841-2-1		87	-	95	3	no-load
Makita	DA3000R	Angle Drill	IA/IA	2,5	1,5	62841-2-1			82	93	3	no-load
Makita	DA3010 DA3010F	Angle Drill	IA	2,5	1,5	EN62841-2-1		84	-	92	3	no-load
Makita	DA3011F	Angle Drill	IA	2,5	1,5	EN62841-2-1		84	-	92	3	no-load
Makita	DA302D	Cordless Drill	IA/IA	2,5	1,5	62841-2-1			70	-	3	no-load
Makita	DA312D	Cordless Drill	IA/IA	2,5	1,5	62841-2-1			70	-	3	no-load
Makita	DA330D	Cordless Angle Drill	IA/IA	2,5	1,5	62841-2-1			70	-	3	no-load
Makita	DA331D	Cordless Angle Drill	IA/IA	2,5	1,5	62841-2-1			70	-	3	no-load
Makita	DA332D	Cordless Angle Drill	IA/IA	2,5	1,5	EN62841-2-1		72	-	-	3	no-load
Makita	DA333D	Cordless Angle Drill	IA/IA	3,0	1,5	EN62841-2-1		71	-	-	3	no-load
Makita	DA391D	Cordless Drill	IA/IA	2,5	1,5	62841-2-1			71	-	3	no-load
Makita	DA392D	Cordless Drill	IA/IA	2,5	1,5	62841-2-1			70	-	3	no-load
Makita	DA4000LR	Angle Drill	IA/IA	4,6	2,9	EN62841-2-1		83	-	91	3	no-load
Makita	DA4030	Angle Drill	IA/IA	2,5	1,5	62841-2-1			87	98	3	no-load
Makita	DA4031	Angle Drill	IA/IA	2,5	1,5	EN62841-2-1		90	-	98	3	no-load
Makita	DA6301	Drill	IA/IA	2,5	1,5	62841-2-1			90	101	3	no-load

	Makita	DUX18	Pole Saw Attachment EY402MP	Ⅲ	2,7 2,5	1,5	ISO22867(ISO11680-1)			93	102	3	Uncertainty: K_{PA}/K_{WA}	ISO22868(ISO11680-1)	
	Makita	DUX18	Pole Saw Attachment EY402MP	Ⅲ	2,9 2,5	1,5	ISO22867(ISO11680-1)			93	102	3	Uncertainty: K_{PA}/K_{WA}	ISO22868(ISO11680-1)	
	Makita	DUX18	Pole Saw Attachment EY403MP	Ⅲ	3,2 2,5	1,5	ISO22867(ISO11680-1)			93	104	3	Uncertainty: K_{PA}/K_{WA}	ISO22868(ISO11680-1)	
	Makita	DUX18	Pole Saw Attachment EY403MP	Ⅲ	3,7 2,5	1,5	ISO22867(ISO11680-1)			94	103	3	Uncertainty: K_{PA}/K_{WA}	ISO22868(ISO11680-1)	
	Makita	DUX18	Pole Saw Attachment EY402MP + LE400MP	Ⅲ	2,5	1,5	ISO22867(ISO11680-1)			93	102	3	Uncertainty: K_{PA}/K_{WA}	ISO22868(ISO11680-1)	without LE400MP
	Makita	DUX18	Pole Saw Attachment EY402MP + LE400MP	Ⅲ	2,5	1,5	ISO22867(ISO11680-1)			93	102	3	Uncertainty: K_{PA}/K_{WA}	ISO22868(ISO11680-1)	without LE400MP
	Makita	DUX18	Pole Saw Attachment EY403MP + LE400MP	Ⅲ	2,5	1,5	ISO22867(ISO11680-1)			93	104	3	Uncertainty: K_{PA}/K_{WA}	ISO22868(ISO11680-1)	without LE400MP
	Makita	DUX18	Pole Saw Attachment EY403MP + LE400MP	Ⅲ	2,6 2,5	1,5	ISO22867(ISO11680-1)			94	103	3	Uncertainty: K_{PA}/K_{WA}	ISO22868(ISO11680-1)	without LE400MP
	Makita	DUX18	Cultivator Attachment KR400MP	Ⅲ	2,5	1,5	EN709			73,0	83,4	3,2/2,7	Uncertainty: K_{PA}/K_{WA}	EN709	
	Makita	DUX18	Cultivator Attachment KR401MP	Ⅲ	2,5	1,5	EN709			73,6	83,2	3,8/2,9	Uncertainty: K_{PA}/K_{WA}	EN709	
	Makita	DUX18	Power Brush Attachment BR400MP	Ⅲ	2,5	1,5	EN60335-2-72			76,0	86,8	1,3/1,2	Uncertainty: K_{PA}/K_{WA}	EN60335-2-72	p at Operators ea
	Makita	DUX18	Power Sweep Attachment SW400MP	Ⅲ	2,6 2,5	1,5	EN60335-2-72			76,2	85,8	0,2/0,7	Uncertainty: K_{PA}/K_{WA}	EN60335-2-72	p at Operators ea
	Makita	DUX18	Pump Attachment PF400MP	Ⅲ	2,5	1,5	ISO22867			70	86	2,5	Uncertainty: K_{PA}/K_{WA}	ISO20361	
	Makita	DUX18	Pump Attachment PF400MP		-	-	-			-	86,4	1,7	Guaranteed-88-dB	2000/14/EC	
	Makita	DUX18	Snow Blower Attachment SN400MP	Ⅲ	2,5	1,5	ISO8437-4		-	78	-	3		ISO11201(ISO8437-4)	
	Makita	DUX18	Snow Blower Attachment SN400MP		-	-	-			-	90	2,0	Guaranteed-92-dB	ISO3744(ISO8437-4) 2000/14/EC	
	Makita	DUX18	Blower Attachment UB400MP		4,2 2,8	2,2 1,2	EN50636-2-100			85,3	99,5	1,7/1,2	Uncertainty: K_{PA}/K_{WA}	EN50636-2-100	
	Makita	DUX18	Blower Attachment UB400MP		-	-	-			-	99,5	-	Guaranteed-101-dB	2000/14/EC	
	Makita	DUX18	Blower Attachment UB401MP	Ⅲ	2,8 2,5	1,6 1,5	EN50636-2-100			81,2	90,9	1,1/1,3	Uncertainty: K_{PA}/K_{WA}	EN50636-2-100	
	Makita	DUX18	Blower Attachment UB401MP		-	-	-			-	90,9	1,3	Guaranteed-92-dB	2000/14/EC	
	Makita	DUX18	Blower Attachment UB402MP	Ⅲ	2,5	1,5	EN50636-2-100			80,4	90,4	1,7/1,8	Uncertainty: K_{PA}/K_{WA}	EN50636-2-100	
	Makita	DUX18	Blower Attachment UB402MP		-	-	-			-	90,6	1,6	Guaranteed-92-dB	2000/14/EC	
	Makita	DUX18	Blower Attachment UB403MP	Ⅲ	2,5	1,5	EN IEC 62841-4-6		-	87	-	3	Uncertainty: K_{PA}	EN IEC 62841-4-6	
	Makita	DUX18	Blower Attachment UB403MP		-	-	-			-	97	2,1	Guaranteed-99-dB	EN IEC 62841-4-6	
	Makita	DUX18	Blower Attachment UB403MP		-	-	-			-	94,4	2,6	Guaranteed-97-dB	2000/14/EC+2024/1208/EU	
	Makita	DUX18	Blower Attachment UB403MP	Ⅲ	2,5	1,5	EN IEC 62841-4-6		-	95	-	3	Uncertainty: K_{PA}	EN IEC 62841-4-6	
	Makita	DUX18	Blower Attachment UB403MP		-	-	-			-	97	2,1	Guaranteed-100-dB	EN IEC 62841-4-6	
	Makita	DUX18	Weeding Attachment WA400MP	Ⅲ	2,8 2,5	1,5	ISO22867(ISO11806-1)		-	73	88	3	Uncertainty: K_{PA}/K_{WA}	ISO22868(ISO11806-1)	ng blade 220(7253
	Makita	DUX18	Weeding Attachment WA400MP		-	-	-		-	-	87,6	2,5	Guaranteed-90-dB	2000/14/EC	ng blade 220(7253
	Makita	DUX60	Edger Attachment EE400MP	Ⅲ	2,5 2,5	1,5 1,5	ISO11789			74,8	88,2	1,5/2,6	Uncertainty: K_{PA}/K_{WA}	ISO11789	
	Makita	DUX60	Edger Attachment EE400MP		-	-	-			-	88,2	-	Guaranteed-91-dB	2000/14/EC	
	Makita	DUX60	Brushcutter Attachment EM401MP	Ⅲ	3,0 2,5	1,5 1,5	EN11806			78,5	90,2	1,0/1,5	Uncertainty: K_{PA}/K_{WA}	EN11806	
	Makita	DUX60	Brushcutter Attachment EM401MP		-	-	-			-	90,2	-	Guaranteed-92-dB	2000/14/EC	
	Makita	DUX60	String Trimmer Attachment EM401MP	Ⅲ	5,0 2,5	1,5 1,5	EN50636-2-91			84,3	93,3	0,6/1,6	Uncertainty: K_{PA}/K_{WA}	EN50636-2-91	
	Makita	DUX60	String Trimmer Attachment EM401MP		-	-	-			-	93,7	1,5	Guaranteed-96-dB	2000/14/EC	
	Makita	DUX60	String Trimmer Attachment EM401MP	Ⅲ	3,4 2,5	1,5 1,5	ISO22867(ISO11806-1)			79,8	93,0	1,9/2,0	Uncertainty: K_{PA}/K_{WA}	ISO22868(ISO11806-1)/EN50636-2-91	
	Makita	DUX60	String Trimmer Attachment EM401MP	Ⅲ	2,5 2,5	1,5 1,5	EN50636-2-91			77,0	88,5	1,7/1,8	Uncertainty: K_{PA}/K_{WA}	EN50636-2-91	
	Makita	DUX60	String Trimmer Attachment EM401MP		-	-	-			-	92,3	2,0	Guaranteed-95-dB	2000/14/EC	
	Makita	DUX60	Brushcutter Attachment EM404MP	Ⅲ	3,0 2,5	1,5 1,5	EN11806			82,5	93,3	2,2/2,9	Uncertainty: K_{PA}/K_{WA}	EN11806	
	Makita	DUX60	Brushcutter Attachment EM404MP		-	-	-			-	93,3	-	Guaranteed-96-dB	2000/14/EC	
	Makita	DUX60	String Trimmer Attachment EM404MP	Ⅲ	3,0 2,5	1,5 1,5	EN50636-2-91			84,7	92,8	2,3/1,6	Uncertainty: K_{PA}/K_{WA}	EN50636-2-91	
	Makita	DUX60	String Trimmer Attachment EM404MP		-	-	-			-	91,6	1,5	Guaranteed-94-dB	2000/14/EC	
	Makita	DUX60	String Trimmer Attachment EM404MP	Ⅲ	2,5 2,5	1,5 1,5	EN50636-2-91			76,0	87,7	1,8/1,5	Uncertainty: K_{PA}/K_{WA}	EN50636-2-91	
	Makita	DUX60	String Trimmer Attachment EM404MP		-	-	-			-	89,0	1,2	Guaranteed-91-dB	2000/14/EC	
	Makita	DUX60	String Trimmer Attachment EM406MP	Ⅲ	2,5 2,5	1,5 1,5	EN50636-2-91			84,7	93,5	2,5/2,2	Uncertainty: K_{PA}/K_{WA}	EN50636-2-91	
	Makita	DUX60	String Trimmer Attachment EM406MP		-	-	-			-	91,8	1,7	Guaranteed-96-dB	2000/14/EC	
	Makita	DUX60	String Trimmer Attachment EM406MP	Ⅲ	4,0 2,5	1,5 1,5	EN50636-2-91			77,0	85,6	1,9/2,0	Uncertainty: K_{PA}/K_{WA}	EN50636-2-91	
	Makita	DUX60	String Trimmer Attachment EM406MP		-	-	-			-	89,1	1,1	Guaranteed-91-dB	2000/14/EC	
	Makita	DUX60	Brushcutter Attachment EM407MP	Ⅲ	2,5	1,5	ISO22867(ISO11806-1)			83,2	99,3	3,9/2,5	Uncertainty: K_{PA}/K_{WA}	ISO22868(ISO11806-1)	
	Makita	DUX60	Brushcutter Attachment EM407MP		-	-	-			-	99,3	2,5	Guaranteed-102-dB	2000/14/EC	
	Makita	DUX60	String Trimmer Attachment EM408MP	Ⅲ	2,5	1,5	ISO22867(ISO11806-1)			79,9	94,5	2,6/2,0	Uncertainty: K_{PA}/K_{WA}	ISO22868(ISO11806-1)	230mm Blade 4
	Makita	DUX60	String Trimmer Attachment EM408MP		-	-	-			-	94,5	2,0	Guaranteed-96-dB	2000/14/EC	
	Makita	DUX60	String Trimmer Attachment EM408MP	Ⅲ	2,5	1,5	ISO22867(ISO11806-1)			79,0	91,8	2,6/1,7	Uncertainty: K_{PA}/K_{WA}	ISO22868(ISO11806-1)/EN50636-2-91	head 96-M10L(12
	Makita	DUX60	String Trimmer Attachment EM408MP		-	-	-			-	90,9	1,4	Guaranteed-93-dB	2000/14/EC	

	Makita	DUX60	String Trimmer Attachment EM408MP	≤	2,5	1,5	ISO22867(ISO11806-1)			80,1	91,0	0,7/1,6	Uncertainty: K_{PA}/K_{WA}	ISO22868(ISO11806-1)EN50636-2-91	blade assembly(12
	Makita	DUX60	String Trimmer Attachment EM408MP		-	-	-			-	90,9	2,0	Guaranteed: -93-dB	2000/14/EC	
	Makita	DUX60	String Trimmer Attachment EM409MP	≤	2,5	1,5	ISO22867(ISO11806-1)			79,9	92,7	2,3/0,9	Uncertainty: K_{PA}/K_{WA}	ISO22868(ISO11806-1)EN50636-2-91	head 96-M10L(12
	Makita	DUX60	String Trimmer Attachment EM409MP		-	-	-			-	91,8	1,0	Guaranteed: -93-dB	2000/14/EC	
	Makita	DUX60	String Trimmer Attachment EM409MP	≤	2,5	1,5	ISO22867(ISO11806-1)			80,3	91,2	0,9/2,2	Uncertainty: K_{PA}/K_{WA}	ISO22868(ISO11806-1)EN50636-2-91	blade assembly(12
	Makita	DUX60	String Trimmer Attachment EM409MP		-	-	-			-	91,3	2,7	Guaranteed: -94-dB	2000/14/EC	
	Makita	DUX60	Pole Hedge Trimmer Attachment EN401MP		8,7	1,5	EN62841-4-2		-	85	-	3	Uncertainty: K_{PA}	EN62841-4-2	
	Makita	DUX60	Pole Hedge Trimmer Attachment EN401MP		4,2	1,5	-			-	93	0,7	Guaranteed: -93-dB	EN62841-4-2	
	Makita	DUX60	Pole Hedge Trimmer Attachment EN401MP		-	-	-			-	92,6	0,7	Guaranteed: -93-dB	2000/14/EC	
	Makita	DUX60	Pole Hedge Trimmer Attachment EN401MP		5,9	1,5	EN62841-4-2		-	82	-	3	Uncertainty: K_{PA}	EN62841-4-2	
	Makita	DUX60	Pole Hedge Trimmer Attachment EN401MP + LE400MP		4,4	1,5	-			-	93	1,1	Guaranteed: -94-dB	EN62841-4-2	
	Makita	DUX60	Pole Hedge Trimmer Attachment EN401MP + LE400MP		-	-	-			-	92,8	1,1	Guaranteed: -94-dB	2000/14/EC	
	Makita	DUX60	Pole Hedge Trimmer Attachment EN401MP + LE400MP		-	-	-			-	92,8	1,1	Guaranteed: -94-dB	2000/14/EC	
	Makita	DUX60	Pole Hedge Trimmer Attachment EN402MP	≤	2,5	1,5	EN62841-4-2		-	82	-	3	Uncertainty: K_{PA}	EN62841-4-2	
	Makita	DUX60	Pole Hedge Trimmer Attachment EN402MP		-	-	-			-	92	2,5	Guaranteed: -94-dB	EN62841-4-2	
	Makita	DUX60	Pole Hedge Trimmer Attachment EN402MP		-	-	-			-	91,9	2,7	Guaranteed: -95-dB	2000/14/EC	
	Makita	DUX60	Pole Hedge Trimmer Attachment EN402MP		4,4	1,5	EN62841-4-2		-	79	-	3	Uncertainty: K_{PA}	EN62841-4-2	
	Makita	DUX60	Pole Hedge Trimmer Attachment EN402MP+LE400MP		2,7	-	-			-	93	1,9	Guaranteed: -95-dB	EN62841-4-2	
	Makita	DUX60	Pole Hedge Trimmer Attachment EN402MP+LE400MP		-	-	-			-	92,9	2,0	Guaranteed: -95-dB	2000/14/EC	
	Makita	DUX60	Pole Hedge Trimmer Attachment EN402MP+LE400MP		-	-	-			-	92,9	2,0	Guaranteed: -95-dB	2000/14/EC	
	Makita	DUX60	Pole Hedge Trimmer Attachment EN410MP		5,8	1,5	EN62841-4-2		-	81	-	3	Uncertainty: K_{PA}	EN62841-4-2	
	Makita	DUX60	Pole Hedge Trimmer Attachment EN410MP		3,4	1,5	-			-	88	2,2	Guaranteed: -90-dB	EN62841-4-2	
	Makita	DUX60	Pole Hedge Trimmer Attachment EN410MP		-	-	-			-	88,2	2,2	Guaranteed: -90-dB	2000/14/EC	
	Makita	DUX60	Pole Hedge Trimmer Attachment EN410MP + LE400MP		4,6	1,5	EN62841-4-2		-	79	-	3	Uncertainty: K_{PA}	EN62841-4-2	
	Makita	DUX60	Pole Hedge Trimmer Attachment EN410MP + LE400MP		2,8	1,5	-			-	88	2,7	Guaranteed: -91-dB	EN62841-4-2	
	Makita	DUX60	Pole Hedge Trimmer Attachment EN410MP + LE400MP		-	-	-			-	88,3	2,7	Guaranteed: -91-dB	2000/14/EC	
	Makita	DUX60	Ground Trimmer Attachment EN420MP		6,7	1,5	EN62841-4-2		-	84	-	3	Uncertainty: K_{PA}	EN62841-4-2	
	Makita	DUX60	Ground Trimmer Attachment EN420MP		4,2	1,5	-			-	94	0,7	Guaranteed: -95-dB	EN62841-4-2	
	Makita	DUX60	Ground Trimmer Attachment EN420MP		-	-	-			-	94,0	0,7	Guaranteed: -95-dB	2000/14/EC	
	Makita	DUX60	Ground Trimmer Attachment EN421MP		6,5	1,5	ISO10517			84,0	94,0	0,8/0,7	Uncertainty: K_{PA}/K_{WA}	ISO10517	
	Makita	DUX60	Ground Trimmer Attachment EN421MP		4,0	1,5	-			-	94,0	-	Guaranteed: -95-dB	2000/14/EC	
	Makita	DUX60	Ground Trimmer Attachment EN422MP	≤	2,5	1,5	EN62841-4-2		-	81	-	3	Uncertainty: K_{PA}	EN62841-4-2	
	Makita	DUX60	Ground Trimmer Attachment EN422MP		2,6	-	-			-	91	1,8	Guaranteed: -93-dB	EN62841-4-2	
	Makita	DUX60	Ground Trimmer Attachment EN422MP		-	-	-			-	91,4	1,9	Guaranteed: -93-dB	2000/14/EC	
	Makita	DUX60	Ground Trimmer Attachment EN422MP+LE400MP		-	-	-			-	92,7	1,8	Guaranteed: -95-dB	2000/14/EC	
	Makita	DUX60	Ground Trimmer Attachment EN424MP	≤	2,5	1,5	EN62841-1			77	86	3	Uncertainty: K_{PA}/K_{WA}	EN62841-1	
	Makita	DUX60	Ground Trimmer Attachment (lawnmower)		-	-	-			-	86,6	1,2	Guaranteed: -88-dB	2000/14/EC	
Added	Makita	DUX60	Ground Trimmer Attachment EN425MP	≤	2,5	1,5	EN62841-1			78	88	3	Uncertainty: K_{PA}/K_{WA}	EN62841-1	
	Makita	DUX60	Pole Saw Attachment EY401MP	≤	2,5	1,5	ISO11680-1			92,5	101,9	1,4/1,4	Uncertainty: K_{PA}/K_{WA}	ISO11680-1	
	Makita	DUX60	Pole Saw Attachment EY401MP + LE400MP	≤	2,5	1,5	ISO11680-1			86,6	101,2	1,0/1,0	Uncertainty: K_{PA}/K_{WA}	ISO11680-1	
	Makita	DUX60	Pole Saw Attachment EY402MP	≤	2,7	1,5	ISO22867(ISO11680-1)			94	104	3	Uncertainty: K_{PA}/K_{WA}	ISO22868(ISO11680-1)	
	Makita	DUX60	Pole Saw Attachment EY402MP	≤	2,5	1,5	ISO22867(ISO11680-1)			97	103	3	Uncertainty: K_{PA}/K_{WA}	ISO22868(ISO11680-1)	
	Makita	DUX60	Pole Saw Attachment EY403MP	≤	2,7	1,5	ISO22867(ISO11680-1)			96	105	3	Uncertainty: K_{PA}/K_{WA}	ISO22868(ISO11680-1)	
	Makita	DUX60	Pole Saw Attachment EY403MP	≤	2,5	1,5	ISO22867(ISO11680-1)			96	105	3	Uncertainty: K_{PA}/K_{WA}	ISO22868(ISO11680-1)	
	Makita	DUX60	Pole Saw Attachment EY402MP + LE400MP	≤	2,5	1,5	ISO22867(ISO11680-1)			94	104	3	Uncertainty: K_{PA}/K_{WA}	ISO22868(ISO11680-1)	without LE400MP
	Makita	DUX60	Pole Saw Attachment EY402MP + LE400MP	≤	2,5	1,5	ISO22867(ISO11680-1)			97	103	3	Uncertainty: K_{PA}/K_{WA}	ISO22868(ISO11680-1)	without LE400MP
	Makita	DUX60	Pole Saw Attachment EY403MP + LE400MP	≤	3,0	1,5	ISO22867(ISO11680-1)			96	105	3	Uncertainty: K_{PA}/K_{WA}	ISO22868(ISO11680-1)	without LE400MP
	Makita	DUX60	Pole Saw Attachment EY403MP + LE400MP	≤	2,5	1,5	ISO22867(ISO11680-1)			96	105	3	Uncertainty: K_{PA}/K_{WA}	ISO22868(ISO11680-1)	without LE400MP
	Makita	DUX60	Coffee Harvester Attachment EJ400MP		4,0	1,5	ISO10517			87,4	94,5	1,4/1,3	Uncertainty: K_{PA}/K_{WA}	ISO10517	
	Makita	DUX60	Coffee Harvester Attachment EJ400MP + LE400MP		4,5	1,5	ISO10517			85,6	95,5	1,0/1,3	Uncertainty: K_{PA}/K_{WA}	ISO10517	
	Makita	DUX60	Cultivator Attachment KR400MP	≤	2,5	1,5	EN709			76,7	84,2	2,2/1,0	Uncertainty: K_{PA}/K_{WA}	EN709	
	Makita	DUX60	Cultivator Attachment KR401MP	≤	2,5	1,5	EN709			73,1	84,2	1,4/1,8	Uncertainty: K_{PA}/K_{WA}	EN709	
	Makita	DUX60	Power Brush Attachment BR400MP	≤	2,5	1,5	EN60335-2-72			79,5	89,0	0,9/0,7	Uncertainty: K_{PA}/K_{WA}	EN60335-2-72	ip at Operators ea
	Makita	DUX60	Power Sweep Attachment SW400MP	≤	2,6	1,5	EN60335-2-72			80 1	88,8	1,8/0,7	Uncertainty: K_{PA}/K_{WA}	EN60335-2-72	ip at Operators ea
	Makita	DUX60	Pump Attachment PF400MP	≤	2,5	1,5	ISO22867			72	87	3,9	Uncertainty: K_{PA}/K_{WA}	ISO20361	
	Makita	DUX60	Pump Attachment PF400MP		-	-	-			-	87,2	3,0	Guaranteed: -90-dB	2000/14/EC	

	Makita	DUX60	Snow Blower Attachment SN400MP	≤	2,5	1,5	ISO8437-4		-	77	-	3		ISO11201(ISO8437-4)	
	Makita	DUX60	Snow Blower Attachment SN400MP		-	-	-		-	-	91	2,2	Guaranteed:-93-dB	ISO3744(ISO8437-4) 2000/14/EC	
	Makita	DUX60	Blower Attachment UB400MP	≤	4,5 2,5	2,0 1,5	EN50636-2-100			89,8	100,4	0,4/0,8	Uncertainty: K _{PA} /K _{WA}	EN50636-2-100	
	Makita	DUX60	Blower Attachment UB400MP		-	-	-		-	-	100,4	-	Guaranteed:-101-dB	2000/14/EC	
	Makita	DUX60	Blower Attachment UB400MP		-	-	-		-	96,4	105,3	2,4/1,6	Uncertainty: K _{PA} /K _{WA}	EN50636-2-100	
	Makita	DUX60	Blower Attachment UB400MP		-	-	-		-	-	104,0	1,7	Guaranteed:-106-dB	2000/14/EC	
	Makita	DUX60	Blower Attachment UB401MP	≤	3,6 2,5	1,7 1,5	EN50636-2-100			83,4	94,1	1,1/0,8	Uncertainty: K _{PA} /K _{WA}	EN50636-2-100	
	Makita	DUX60	Blower Attachment UB401MP		-	-	-		-	-	94,1	0,8	Guaranteed:-95-dB	2000/14/EC	
	Makita	DUX60	Blower Attachment UB401MP		-	-	-		-	85,1	97,0	2,1/1,7	Uncertainty: K _{PA} /K _{WA}	EN50636-2-100	
	Makita	DUX60	Blower Attachment UB401MP		-	-	-		-	-	95,9	2,1	Guaranteed:-98-dB	2000/14/EC	
	Makita	DUX60	Blower Attachment UB402MP	≤	2,5	1,5	EN50636-2-100			80,5	90,2	1,6/1,7	Uncertainty: K _{PA} /K _{WA}	EN50636-2-100	
	Makita	DUX60	Blower Attachment UB402MP		-	-	-		-	-	90,5	1,7	Guaranteed:-92-dB	2000/14/EC	
	Makita	DUX60	Blower Attachment UB403MP	≤	2,5	1,5	EN IEC 62841-4-6		-	90	-	3	Uncertainty: K _{PA}	EN IEC 62841-4-6	
	Makita	DUX60	Blower Attachment UB403MP		-	-	-		-	-	100	2,0	Guaranteed:-102-dB	EN IEC 62841-4-6	
	Makita	DUX60	Blower Attachment UB403MP		-	-	-		-	-	97,3	2,4	Guaranteed:-100-dB	2000/14/EC+2024/1208/EU	
	Makita	DUX60	Blower Attachment UB403MP		2,8	1,5	EN IEC 62841-4-6		-	100	-	3	Uncertainty: K _{PA}	EN IEC 62841-4-6	
	Makita	DUX60	Blower Attachment UB403MP		-	-	-		-	-	101	2,0	Guaranteed:-103-dB	EN IEC 62841-4-6	
	Makita	DUX60	Weeding Attachment WA400MP		3,0 2,7	1,5	ISO22867(ISO11806-1)		-	74	88	3	Uncertainty: K _{PA} /K _{WA}	ISO22868(ISO11806-1)	ng blade 220/7253
	Makita	DUX60	Weeding Attachment WA400MP		-	-	-		-	-	87,7	2,2	Guaranteed:-90-dB	2000/14/EC	ng blade 220/7253
	Makita	DVC150L(DVC151L)	Corded and Cordless Vacuum Cleaner	≤	2,5	1,5	60335-2-69		≤	75	-	2,5	Vaccum-test-carpet	60335-2-69	
	Makita	DVC152L(DVC153L DVC154L)	Cordless Vacuum Cleaner	≤	2,5	1,5	60335-2-69		≤	70	-	2,5	Vaccum-test-carpet	60335-2-69	
	Makita	DVC155L(DVC156L DVC157L)	Cordless Vacuum Cleaner	≤	2,5	1,5	60335-2-69		≤	70	-	2,5	Vaccum-test-carpet	60335-2-69	vacuum mode,wid
	Makita	DVC260	Cordless Backpack Vacuum Cleaner	≤	2,5	1,5	60335-2-69		≤	70	-	2,5	Vaccum-test-carpet	60335-2-69,60704-2-1	
	Makita	DVC261 DVC265	Cordless Backpack Vacuum Cleaner	≤	2,5	1,5	60335-2-69		≤	70	-	2,5	Vaccum-test-carpet	60335-2-69,60704-2-1	
	Makita	DVC350	Cordless Vacuum Cleaner	≤	2,5	1,5	60745-1		≤	84	95	3	no-load	60745-1	BLOWER MODE
	Makita	DVC560	Cordless Uplight Cleaner	≤	2,5	1,5	60335-2-69		≤	70	-	2,5	Vaccum-test-carpet	60335-2-69	
	Makita	DVC660 DVC665	Cordless Backpack Vacuum Cleaner	≤	2,5	1,5	60335-2-69		≤	70	-	2,5	Vaccum-test-carpet	60335-2-69,60704-2-1	Lp at Operators ear
	Makita	DVC750L	Cordless Portable Vacuum Cleaner	≤	2,5	1,5	60335-2-69		≤	76	-	2,5	Vaccum-test-carpet	60335-2-69	vacuum mode,wid
	Makita	DVC865L(DVC866L DVC867L)	Cordless Vacuum Cleaner	≤	2,5	1,5	60335-2-69		≤	70	-	2,5	Vaccum-test-carpet	60335-2-69	vacuum mode,wid
	Makita	DVR350	Cordless Concrete Vibrator		8,0	1,5	ENIEC62841-2-12		≤	70	-	3	no-load without flexible hose	ENIEC62841-2-12	
	Makita	DVR450	Cordless Concrete Vibrator		3,7	1,5	ENIEC62841-2-12		≤	70	-	3	no-load without flexible hose	ENIEC62841-2-12	
	Makita	DVR850	Cordless Concrete Vibrator		3,1	1,5	ENIEC62841-2-12		≤	70	-	3	no-load without flexible hose	ENIEC62841-2-12	
	Makita	DWR180	Cordless Ratchet Wrench		2,5	1,5	EN62841-2-2		77	-	-	3	no-load	EN62841-2-2	
	Makita	DWT310	Shear Wrench		0,3	1,5	EN62841-2-2		86	-	94	3	no-load	EN62841-2-2	
	Makita	DX01	Dust Extraction System		13,0	1,5	60745-2-6			91	102	3	hammer-drilling	60745-2-6	
	Makita	DX01	Dust Extraction System		13,0	1,5	60745-2-6			91	102	3	hammer-drilling	60745-2-6	
	Makita	DX02	Dust Extraction System		13,0	1,5	60745-2-6			90	101	3	hammer-drilling	60745-2-6	
	Makita	DX02	Dust Extraction System		13,0	1,5	60745-2-6			90	101	3	hammer-drilling	60745-2-6	
	Makita	EA3201S	Petrol Chain Saw		4,8	2,0	ISO22867			102 6	109 8	2,5/2,5	Uncertainty: K _{PA} /K _{WA}	ISO22868	
	Makita	EA3201S	Petrol Chain Saw		-	-	-			-	111	-	Guaranteed:112-dB	2000/14/EC	
	Makita	EA3500S	Petrol Chain Saw		4,9/5,0	2,0	ISO22867			101 8	111 8	2,5/2,5	Uncertainty: K _{PA} /K _{WA}	ISO22868	EA3500S MKC
	Makita	EA3500S	Petrol Chain Saw		-	-	-			-	111 8	-	Guaranteed:113-dB	2000/14/EC	EA3500S MKC
	Makita	EA3501S	Petrol Chain Saw		4,9/5,0	2,0	ISO22867			101 8	111 8	2,5/2,5	Uncertainty: K _{PA} /K _{WA}	ISO22868	EA3500S MKC
	Makita	EA3501S	Petrol Chain Saw		-	-	-			-	111 8	-	Guaranteed:113-dB	2000/14/EC	EA3500S MKC
	Makita	EA3502S	Petrol Chain Saw		4,9/5,0	2,0	ISO22867			101 8	111 8	2,5/2,5	Uncertainty: K _{PA} /K _{WA}	ISO22868	EA3500S MKC
	Makita	EA3502S	Petrol Chain Saw		-	-	-			-	111 8	-	Guaranteed:113-dB	2000/14/EC	EA3500S MKC
	Makita	EA3503S	Petrol Chain Saw		4,9/5,0	2,0	ISO22867			101 8	111 8	2,5/2,5	Uncertainty: K _{PA} /K _{WA}	ISO22868	EA3500S MKC
	Makita	EA3503S	Petrol Chain Saw		-	-	-			-	111 8	-	Guaranteed:113-dB	2000/14/EC	EA3500S MKC
	Makita	EA3600	Petrol Chain Saw		2,7/2,8	2,0	ISO22867			97,1	109,6	2,5/2,5	Uncertainty: K _{PA} /K _{WA}	ISO22868	
	Makita	EA3600	Petrol Chain Saw		-	-	-			-	109	1,1	Guaranteed:111-dB	2000/14/EC	
	Makita	EA3601	Petrol Chain Saw		2,7/2,8	2,0	ISO22867			97,1	109,6	2,5/2,5	Uncertainty: K _{PA} /K _{WA}	ISO22868	
	Makita	EA3601	Petrol Chain Saw		-	-	-			-	109	1,1	Guaranteed:111-dB	2000/14/EC	
	Makita	EA3700T	Petrol Chain Saw		3,5/3,1	2,0	ISO22867			100,2	109,8	2,0/2,0	Uncertainty: K _{PA} /K _{WA}	ISO22868	
	Makita	EA3700T	Petrol Chain Saw		-	-	-			109 8	109 8	-	Guaranteed:112dB	2000/14/EC	
	Makita	EB2901	Petrol Blower		1,9	0,6	EN15503			92 8	103 7	0,8/0,6	Uncertainty: K _{PA} /K _{WA}	EN15503	
	Makita	EB2901	Petrol Blower		-	-	-			-	103,7	-	Guaranteed:104-dB	2000/14/EC	
	Makita	EB2901	Petrol Blower		2,3	0,9	EN15503			90,8	103,7	0,6/0,8	Uncertainty: K _{PA} /K _{WA}	EN15503	
	Makita	EB2901	Petrol Blower		-	-	-			-	103,7	-	Guaranteed:104-dB	2000/14/EC	
	Makita	EB2901	Petrol Blower		2,4/2,0	0,5/0,4	EN15503			91,2	102,4	1,4/0,7	Uncertainty: K _{PA} /K _{WA}	EN15503	

	Makita	EB2901	Petrol Blower		-	-	-			-	102,4	-	Guaranteed:103-dB	2000/14/EC	
	Makita	EB2902	Petrol Blower		1,9	0,6	EN15503			92,8	103,7	0,8/0,6	Uncertainty: KPA/KWA	EN15503	
	Makita	EB2902	Petrol Blower		-	-	-			-	103,7	-	Guaranteed:104-dB	2000/14/EC	
	Makita	EB2902	Petrol Blower		2,3	0,9	EN15503			90,8	103,7	0,6/0,8	Uncertainty: KPA/KWA	EN15503	
	Makita	EB2902	Petrol Blower		-	-	-			-	103,7	-	Guaranteed:104-dB	2000/14/EC	
	Makita	EB2902	Petrol Blower		2,4/2,0	0,5/0,4	EN15503			91,2	102,4	1,4/0,7	Uncertainty: KPA/KWA	EN15503	
	Makita	EB2902	Petrol Blower		-	-	-			-	102,4	-	Guaranteed:103-dB	2000/14/EC	
	Makita	EB5300TH	Petrol Blower		2,2	0,4	EN15503			95,6	102,4	0,8/1,0	Uncertainty: KPA/KWA	EN15503	
	Makita	EB5300TH	Petrol Blower		-	-	-			-	102,4	-	Guaranteed:103-dB	2000/14/EC	
	Makita	EB5300TH	Petrol Blower		2,5	0,6	EN15503			96,0	102,5	0,4/1,6	Uncertainty: KPA/KWA	EN15503	
	Makita	EB5300TH	Petrol Blower		-	-	-			-	102,5	-	Guaranteed:104-dB	2000/14/EC	
	Makita	EB5300TH	Petrol Blower		2,2	0,4	EN15503			95,6	101,9	0,5/0,5	Uncertainty: KPA/KWA	EN15503	
	Makita	EB5300TH	Petrol Blower		-	-	-			-	101,9	-	Guaranteed:102-dB	2000/14/EC	
	Makita	EB5300TH	Petrol Blower		2,9	0,5	EN15503			95,7	101,7	0,9/1,0	Uncertainty: KPA/KWA	EN15503	
	Makita	EB5300TH	Petrol Blower		-	-	-			-	101,7	-	Guaranteed:102-dB	2000/14/EC	
	Makita	EB5300WH	Petrol Blower		2,3/0,5	0,8/0,3	EN15503			95,6	102,4	0,8/1,0	Uncertainty: KPA/KWA	EN15503	
	Makita	EB5300WH	Petrol Blower		-	-	-			-	102,4	-	Guaranteed:103-dB	2000/14/EC	
	Makita	EB5300WH	Petrol Blower		3,6/0,5	1,9/0,3	EN15503			96,0	102,5	0,4/1,6	Uncertainty: KPA/KWA	EN15503	
	Makita	EB5300WH	Petrol Blower		-	-	-			-	102,5	-	Guaranteed:104-dB	2000/14/EC	
	Makita	EB5300WH	Petrol Blower		2,3/0,5	1,3/0,3	EN15503			95,6	101,9	0,5/0,5	Uncertainty: KPA/KWA	EN15503	
	Makita	EB5300WH	Petrol Blower		-	-	-			-	101,9	-	Guaranteed:102-dB	2000/14/EC	
	Makita	EB5300WH	Petrol Blower		4,0/0,5	0,8/0,2	EN15503			95,7	101,7	0,9/1,0	Uncertainty: KPA/KWA	EN15503	
	Makita	EB5300WH	Petrol Blower		-	-	-			-	101,7	-	Guaranteed:102-dB	2000/14/EC	
	Makita	EB7650TH	Petrol Blower		2,5	1,8	EN15503			100	110	0,9/0,8	Uncertainty: KPA/KWA	EN15503	Blow nozzle
	Makita	EB7650TH	Petrol Blower		-	-	-			-	110	-	Guaranteed:111-dB	2000/14/EC	Blow nozzle
	Makita	EB7650TH	Petrol Blower		2,3	1,6	EN15503			100	110	0,7/0,8	Uncertainty: KPA/KWA	EN15503	
	Makita	EB7650TH	Petrol Blower		-	-	-			-	110	-	Guaranteed:111-dB	2000/14/EC	
	Makita	EB7650TH	Petrol Blower		4,1	2,2	EN15503			100	110	1,2/0,6	Uncertainty: KPA/KWA	EN15503	Flat Nozzle
	Makita	EB7650TH	Petrol Blower		-	-	-			-	110	-	Guaranteed:111-dB	2000/14/EC	Flat Nozzle
	Makita	EB7650WH	Petrol Blower		2,7/0,7	2,1/0,5	EN15503			100	110	1,2/0,6	Uncertainty: KPA/KWA	EN15503	Blow nozzle
	Makita	EB7650WH	Petrol Blower		-	-	-			-	110	-	Guaranteed:111-dB	2000/14/EC	Blow nozzle
	Makita	EB7650WH	Petrol Blower		2,3/0,7	2,1/0,4	EN15503			100	110	1,3/0,5	Uncertainty: KPA/KWA	EN15503	
	Makita	EB7650WH	Petrol Blower		-	-	-			-	110	-	Guaranteed:111-dB	2000/14/EC	
	Makita	EB7650WH	Petrol Blower		4,8/0,9	3/0,4	EN15503			100	110	1,4/0,7	Uncertainty: KPA/KWA	EN15503	Flat Nozzle
	Makita	EB7650WH	Petrol Blower		-	-	-			-	110	-	Guaranteed:111-dB	2000/14/EC	Flat Nozzle
	Makita	EB7660TH	Petrol Blower		2,3	1,2	EN15503			102 8	110 6	1,6/0,8	Uncertainty: KPA/KWA	EN15503	
	Makita	EB7660TH	Petrol Blower		-	-	-			-	110 6	-	Guaranteed:111dB	2000/14/EC	
	Makita	EB7660TH	Petrol Blower		3,5	0,8	EN15503			102 5	110 7	1,8/0,7	Uncertainty: KPA/KWA	EN15503	
	Makita	EB7660TH	Petrol Blower		-	-	-			-	110 7	-	Guaranteed:111-dB	2000/14/EC	
	Makita	EB7660TH	Petrol Blower		2,3	1,0	EN15503			102 5	110 4	1,4/0,6	Uncertainty: KPA/KWA	EN15503	
	Makita	EB7660TH	Petrol Blower		-	-	-			-	110 4	-	Guaranteed:111-dB	2000/14/EC	
	Makita	EB7660TH	Petrol Blower		3,4	1,1	EN15503			102 1	109 7	2,2/0,3	Uncertainty: KPA/KWA	EN15503	
	Makita	EB7660TH	Petrol Blower		-	-	-			-	109 7	-	Guaranteed:110-dB	2000/14/EC	
	Makita	EB7660WH	Petrol Blower		3,0/0,7	1,2/0,5	EN15503			102 8	110 6	1,6/0,8	Uncertainty: KPA/KWA	EN15503	
	Makita	EB7660WH	Petrol Blower		-	-	-			-	110 6	-	Guaranteed:111-dB	2000/14/EC	
	Makita	EB7660WH	Petrol Blower		4,5/0,6	1,7/0,4	EN15503			102 5	110 7	1,8/0,7	Uncertainty: KPA/KWA	EN15503	
	Makita	EB7660WH	Petrol Blower		-	-	-			-	110 7	-	Guaranteed:111-dB	2000/14/EC	
	Makita	EB7660WH	Petrol Blower		3,0/0,8	1,5/0,7	EN15503			102 5	110 4	1,4/0,6	Uncertainty: KPA/KWA	EN15503	
	Makita	EB7660WH	Petrol Blower		-	-	-			-	110 4	-	Guaranteed:111-dB	2000/14/EC	
	Makita	EB7660WH	Petrol Blower		4,5/0,6	2,0/0,3	EN15503			102 1	109 7	2,2/0,3	Uncertainty: KPA/KWA	EN15503	
	Makita	EB7660WH	Petrol Blower		-	-	-			-	109 7	-	Guaranteed:110-dB	2000/14/EC	
	Makita	EBH341L	Petrol Brushcutter		6,1/7,4	2/0,63	ISO22867			98 2	106 7	0.82/0.38	Uncertainty: K _{PA} /K _{WA}	ISO22868	
	Makita	EBH341L	Petrol Brushcutter		-	-	-			-	109 7	-	Guaranteed:***-dB	2000/14/EC	
	Makita	EE2650H	Petrol Edger		3,7/8,8	2,2/1,8	ISO22867			88,6	98,4	2,3/2,2	Uncertainty: KPA/KWA	ISO22868	

	Makita	EE2650H	Petrol Edger		-	-	-			-	98,4	-	Guaranteed:101-dB	2000/14/EC	
	Makita	EH5000W	Petrol Hedge Trimmer		5,9/3,7	1,7/1,7	EN ISO 10517(IISO22867)			93,0	104,5	1,4/1,2	Uncertainty: K _{PN} /K _{WA}	EN ISO 10517(IISO22868)	
	Makita	EH5000W	Petrol Hedge Trimmer		-	-	-			-	104,0	-	Guaranteed:-106dB	2000/14/EC	
	Makita	EH6000S	Petrol Hedge Trimmer		5,3/3,1	1,8/0,8	EN ISO 10517(IISO22867)			92,7	104,9	3,2/0,9	Uncertainty: K _{PN} /K _{WA}	EN ISO 10517(IISO22868)	
	Makita	EH6000S	Petrol Hedge Trimmer		4,8/3,0	1,0/0,5	EN ISO 10517(IISO22867)			-	102,7	-	Guaranteed:-105dB	2000/14/EC	
	Makita	EH6000W	Petrol Hedge Trimmer		5,3/3,4	2,2/1,8	EN ISO 10517(IISO22867)			92,8	104,4	2,2/1,2	Uncertainty: K _{PN} /K _{WA}	EN ISO 10517(IISO22868)	
	Makita	EH6000W	Petrol Hedge Trimmer		-	-	-			-	104,2	-	Guaranteed:-106dB	2000/14/EC	
	Makita	EH7500S	Petrol Hedge Trimmer		4,7/2,9	2,4/1,3	EN ISO 10517(IISO22867)			94,3	104,9	3,2/1,4	Uncertainty: K _{PN} /K _{WA}	EN ISO 10517(IISO22868)	
	Makita	EH7500S	Petrol Hedge Trimmer		5,9/3,1	0,4/1,7	EN ISO 10517(IISO22867)			-	102,7	-	Guaranteed:-105dB	2000/14/EC	
	Makita	EH7500W	Petrol Hedge Trimmer		3,1/3,0	0,5/1,3	EN ISO 10517(IISO22867)			93,9	104,4	1,2/0,8	Uncertainty: K _{PN} /K _{WA}	EN ISO 10517(IISO22868)	
	Makita	EH7500W	Petrol Hedge Trimmer		-	-	-			-	104,8	-	Guaranteed:-106dB	2000/14/EC	
	Makita	EK6101	Power Cutter		2,7/3,5	2,0/2,0	EN ISO 19432			99,6	108,6	2,5/2,5	Uncertainty: K _{PN} /K _{WA}	EN ISO 19432	
	Makita	EK6101	Power Cutter		-	-	-			-	-	-	Guaranteed:-dB	2000/14/EC	
	Makita	EK7650H	Power Cutter		2,7/1,8	2,0/2,0	EN ISO 19432			92,7	104,6	2,5/2,5	Uncertainty: K _{PN} /K _{WA}	EN ISO 19432	
	Makita	EK7650H	Power Cutter		-	-	-			-	113	-	Guaranteed:-114-dB	2000/14/EC	
	Makita	EK7651H	Power Cutter		2,7/1,8	2,0/2,0	EN ISO 19432			92,7	104,6	2,5/2,5	Uncertainty: K _{PN} /K _{WA}	EN ISO 19432	
	Makita	EK7651H	Power Cutter		-	-	-			-	113	-	Guaranteed:-114-dB	2000/14/EC	
	Makita	ELM3310	Lawn Mower	≤	2,5	1,5	60335-2-77			80	-	2,42		60335-2-77	
	Makita	ELM3310	Lawn Mower		-	-	-			-	87,2	-	Guaranteed:-96-dB	2000/14/EC	
	Makita	ELM3320	Lawn Mower	≤	2,5	1,5	EN IEC 62841-4-3	-		83	-	3		EN IEC 62841-4-3	
	Makita	ELM3320	Lawn Mower		-	-	-			-	91,9	0,7	Guaranteed:-96-dB	EN IEC 62841-4-3	
	Makita	ELM3320	Lawn Mower		-	-	-			-	91,9	0,7	Guaranteed:-96-dB	2000/14/EC	
	Makita	ELM3710	Lawn Mower	≤	2,5	1,5	60335-2-77			83	-	2,35		60335-2-77	
	Makita	ELM3710	Lawn Mower		-	-	-			-	88,7	-	Guaranteed:-96-dB	2000/14/EC	
	Makita	ELM3720	Lawn Mower	≤	2,5	1,5	EN IEC 62841-4-3	-		81	-	3		EN IEC 62841-4-3	
	Makita	ELM3720	Lawn Mower		-	-	-			-	92,8	1,3	Guaranteed:-96-dB	EN IEC 62841-4-3	
	Makita	ELM3720	Lawn Mower		-	-	-			-	92,8	1,3	Guaranteed:-96-dB	2000/14/EC	
	Makita	ELM4110	Lawn Mower	≤	2,5	1,5	60335-2-77			83	-	2,38		60335-2-77	
	Makita	ELM4110	Lawn Mower		-	-	-			-	91,4	-	Guaranteed:-96-dB	2000/14/EC	
	Makita	ELM4120	Lawn Mower	≤	2,5	1,5	EN IEC 62841-4-3	-		84	-	3		EN IEC 62841-4-3	
	Makita	ELM4120	Lawn Mower		-	-	-			-	94,2	1,4	Guaranteed:-96-dB	EN IEC 62841-4-3	
	Makita	ELM4120	Lawn Mower		-	-	-			-	94,2	0,7	Guaranteed:-96-dB	2000/14/EC	
	Makita	ELM4121	Lawn Mower	≤	2,5	1,5	EN IEC 62841-4-3	-		84	-	3		EN IEC 62841-4-3	
	Makita	ELM4121	Lawn Mower		-	-	-			-	94,2	1,4	Guaranteed:-96-dB	EN IEC 62841-4-3	
	Makita	ELM4121	Lawn Mower		-	-	-			-	94,2	0,7	Guaranteed:-96-dB	2000/14/EC	
	Makita	ELM4610	Lawn Mower	≤	2,5	1,5	60335-2-77			87	-	2,4		60335-2-77	
	Makita	ELM4610	Lawn Mower		-	-	-			-	93,3	-	Guaranteed:-96-dB	2000/14/EC	
	Makita	ELM4611	Lawn Mower	≤	2,5	1,5	60335-2-77			87	-	2,4		60335-2-77	
	Makita	ELM4611	Lawn Mower		-	-	-			-	93,3	-	Guaranteed:-96-dB	2000/14/EC	
	Makita	ELM4620	Lawn Mower	≤	2,5	1,5	EN IEC 62841-4-3	-		83	-	3		EN IEC 62841-4-3	
	Makita	ELM4620	Lawn Mower		-	-	-			-	92,7	0,8	Guaranteed:-96-dB	EN IEC 62841-4-3	
	Makita	ELM4620	Lawn Mower		-	-	-			-	92,7	0,8	Guaranteed:-96-dB	2000/14/EC	
	Makita	ELM4621	Lawn Mower	≤	2,5	1,5	EN IEC 62841-4-3	-		83	-	3		EN IEC 62841-4-3	
	Makita	ELM4621	Lawn Mower		-	-	-			-	92,7	0,8	Guaranteed:-96-dB	EN IEC 62841-4-3	
	Makita	ELM4621	Lawn Mower		-	-	-			-	92,7	0,8	Guaranteed:-96-dB	2000/14/EC	
	Makita	EM2100U	Petrol Brushcutter		3,4/4,2	1,7/1,6	ISO22867			90 9	103 6	2,7/2,2	Uncertainty: K _{PA} /K _{WA}	ISO22868	
	Makita	EM2100U	Petrol Brushcutter		-	-	-			-	103 6	-	Guaranteed:106dB	2000/14/EC	
	Makita	EM2100W	Petrol Brushcutter		4,4/4,2	1,0/1,5	ISO22867			92 6	103 6	0,8/2,0	Uncertainty: K _{PA} /K _{WA}	ISO22868	
	Makita	EM2100W	Petrol Brushcutter		-	-	-			-	103 6	-	Guaranteed:106dB	2000/14/EC	
	Makita	EM2101U	Petrol Brushcutter		4,6/5,1	1,9/1,6	ISO22867			91 0	103 1	0,9/0,3	Uncertainty: K _{PA} /K _{WA}	ISO22868	
	Makita	EM2101U	Petrol Brushcutter		-	-	-			-	103 1	-	Guaranteed:103dB	2000/14/EC	
	Makita	EM2102L	Petrol Brushcutter		5,3/4,5	1,6/1,0	ISO22867			90 0	104 3	0,8/1,9	Uncertainty: K _{PA} /K _{WA}	ISO22868	
	Makita	EM2102L	Petrol Brushcutter		-	-	-			-	104 3	-	Guaranteed:106dB	2000/14/EC	
	Makita	EM2102U	Petrol Brushcutter		4,8/5,6	1,6/1,0	ISO22867			90 7	103 8	1,5/0,8	Uncertainty: K _{PA} /K _{WA}	ISO22868	

	Makita	EM2102U	Petrol Brushcutter		-	-	-			-	103 8	-	Guaranteed:105dB	2000/14/EC	
	Makita	EM2510LH	Petrol Brushcutter		5,2/5,0	1,7/1,3	ISO22867			89 6	100 7	2,9/1,7	Uncertainty: K _{PN} /K _{WA}	ISO22868	
	Makita	EM2510LH	Petrol Brushcutter		-	-	-			-	100 7	-	Guaranteed:102-dB	2000/14/EC	
	Makita	EM2510LH	Petrol Brushcutter		5,0/6,0	1,7/1,5	ISO22867			93 2	110 3	1,9/1,1	Uncertainty: K _{PN} /K _{WA}	ISO22868	
	Makita	EM2510LH	Petrol Brushcutter		-	-	-			-	110 3	-	Guaranteed:111-dB	2000/14/EC	
	Makita	EM2510LHC	Petrol Brushcutter		5,3/5,8	1,7/2,0	ISO22867			92 9	110 6	2,9/1,3	Uncertainty: K _{PN} /K _{WA}	ISO22868	
	Makita	EM2510LHC	Petrol Brushcutter		-	-	-			-	110 6	-	Guaranteed:112-dB	2000/14/EC	
	Makita	EM2511LH	Petrol Brushcutter		5,2/5,0	1,7/1,3	ISO22867			89 6	100 7	2,9/1,7	Uncertainty: K _{PN} /K _{WA}	ISO22868	
	Makita	EM2511LH	Petrol Brushcutter		-	-	-			-	100 7	-	Guaranteed:102-dB	2000/14/EC	
	Makita	EM2511LH	Petrol Brushcutter		5,0/6,0	1,7/1,5	ISO22867			93 2	110 3	1,9/1,1	Uncertainty: K _{PN} /K _{WA}	ISO22868	
	Makita	EM2511LH	Petrol Brushcutter		-	-	-			-	110 3	-	Guaranteed:111-dB	2000/14/EC	
	Makita	EM2511LHC	Petrol Brushcutter		5,3/5,8	1,7/2,0	ISO22867			92 9	110 6	2,9/1,3	Uncertainty: K _{PN} /K _{WA}	ISO22868	
	Makita	EM2511LHC	Petrol Brushcutter		-	-	-			-	110 6	-	Guaranteed:112-dB	2000/14/EC	
	Makita	EM2650L attached	Pole Hedge Trimmer Attachment [A-89]		-	-	-			91,7	101,7	1,2/0,7	Uncertainty: K _{PN} /K _{WA}	ISO22868	
	Makita	EM2650L attached	Pole Hedge Trimmer Attachment [A-89]		-	-	-			-	101,7	-	Guaranteed:103-dB	2000/14/EC	
	Makita	EM2650L attached	Hedge Trimmer Attachment		9,7/9,7	2,01,4	EN ISO 10517/(ISO22867)			90,0	104,3	0,9/3,8	Uncertainty: K _{PN} /K _{WA}	EN ISO 10517/(ISO22868)	
	Makita	EM2650L attached	Hedge Trimmer Attachment		-	-	-			-	103,7	0,3	Guaranteed:-104-dB	2000/14/EC	
	Makita	EM2650LH	Petrol Brushcutter		5,1/4,1	0,2/0,4	ISO22867			96 6	105 5	0,9/1,3	Uncertainty: K _{PN} /K _{WA}	ISO22868	
	Makita	EM2650LH	Petrol Brushcutter		-	-	-			-	108 5	-	Guaranteed:111-dB	2000/14/EC	
	Makita	EM2650LHN	Petrol String Trimmer		5,0/5,3	0,8/0,4	ISO22867			91 6	101 6	3,1/2,0	Uncertainty: K _{PA} /K _{WA}	ISO22868	
	Makita	EM2650LHN	Petrol String Trimmer		-	-	-			-	101 6	-	Guaranteed:104dB	2000/14/EC	
	Makita	EM2650UH	Petrol Brushcutter		2,6/2,3	0,8/0,5	ISO22867			96 6	105 5	0,9/1,3	Uncertainty: K _{PN} /K _{WA}	ISO22868	
	Makita	EM2650UH	Petrol Brushcutter		-	-	-			-	108 5	-	Guaranteed:111-dB	2000/14/EC	
	Makita	EM2651L attached	Hedge Trimmer Attachment		9,7/9,7	2,01,4	EN ISO 10517/(ISO22867)			90,0	104,3	0,9/3,8	Uncertainty: K _{PN} /K _{WA}	EN ISO 10517/(ISO22868)	
	Makita	EM2651L attached	Hedge Trimmer Attachment		-	-	-			-	103,7	0,3	Guaranteed:-104-dB	2000/14/EC	
	Makita	EM2651LH	Petrol Brushcutter		5,5/4,4	1,0/0,4	ISO22867			96 6	105 5	0,9/1,3	Uncertainty: K _{PN} /K _{WA}	ISO22868	
	Makita	EM2651LH	Petrol Brushcutter		-	-	-			-	108 5	-	Guaranteed:111-dB	2000/14/EC	
	Makita	EM2651UH	Petrol Brushcutter		2,5/2,4	0,5/0,2	ISO22867			96 6	105 5	0,9/1,3	Uncertainty: K _{PN} /K _{WA}	ISO22868	
	Makita	EM2651UH	Petrol Brushcutter		-	-	-			-	108 5	-	Guaranteed:111-dB	2000/14/EC	
	Makita	EM2652LHN	Petrol String Trimmer		4,9/4,2	1,8/1,6	ISO22867			90	99 4	1,7/3,1	Uncertainty: K _{PA} /K _{WA}	ISO22868	
	Makita	EM2652LHN	Petrol String Trimmer		-	-	-			-	99 4	-	Guaranteed:102dB	2000/14/EC	
	Makita	EM2653L attached	Hedge Trimmer Attachment		9,5/6,1	2,1/1,8	EN ISO 10517/(ISO22867)			89,8	104,3	1,1/3,8	Uncertainty: K _{PN} /K _{WA}	EN ISO 10517/(ISO22868)	
	Makita	EM2653L attached	Hedge Trimmer Attachment		-	-	-			-	102,9	0,8	Guaranteed:-104-dB	2000/14/EC	
	Makita	EM2653LH	Petrol Brushcutter		4,0/4,6	0,6/1,3	ISO22867			94 8	111 3	0,9/1,3	Uncertainty: K _{PN} /K _{WA}	ISO22868	
	Makita	EM2653LH	Petrol Brushcutter		-	-	-			-	111 3	-	Guaranteed:113dB	2000/14/EC	
	Makita	EM2653LH	Petrol Brushcutter		4,6/4,8	1,1/2,1	ISO22867			92 1	105	2,7/1,5	Uncertainty: K _{PN} /K _{WA}	ISO22868	
	Makita	EM2653LH	Petrol Brushcutter		-	-	-			-	105	-	Guaranteed:107dB	2000/14/EC	
	Makita	EM2653LHC	Petrol String Trimmer		4,1/3,9	1,0/2,0	ISO22867			95 6	110 4	2,2/0,8	Uncertainty: K _{PN} /K _{WA}	ISO22868	
	Makita	EM2653LHC	Petrol String Trimmer		-	-	-			-	110 4	-	Guaranteed:111dB	2000/14/EC	
	Makita	EM2653LHN	Petrol String Trimmer		4,5/3,3	1,4/1,1	ISO22867			95 9	111 1	2,2/1,3	Uncertainty: K _{PN} /K _{WA}	ISO22868	
	Makita	EM2653LHN	Petrol String Trimmer		-	-	-			-	111 1	-	Guaranteed:112dB	2000/14/EC	
	Makita	EM2654L attached	Hedge Trimmer Attachment		9,5/6,1	2,1/1,8	EN ISO 10517/(ISO22867)			89,8	104,3	1,1/3,8	Uncertainty: K _{PN} /K _{WA}	EN ISO 10517/(ISO22868)	
	Makita	EM2654L attached	Hedge Trimmer Attachment		-	-	-			-	102,9	0,8	Guaranteed:-104-dB	2000/14/EC	
	Makita	EM2654LH	Petrol Brushcutter		4,0/4,6	0,6/1,3	ISO22867			94 8	111 3	0,9/1,3	Uncertainty: K _{PN} /K _{WA}	ISO22868	
	Makita	EM2654LH	Petrol Brushcutter		-	-	-			-	111 3	-	Guaranteed:113dB	2000/14/EC	
	Makita	EM2654LH	Petrol Brushcutter		4,6/4,8	1,1/2,1	ISO22867			92 1	105	2,7/1,5	Uncertainty: K _{PN} /K _{WA}	ISO22868	
	Makita	EM2654LH	Petrol Brushcutter		-	-	-			-	105	-	Guaranteed:107dB	2000/14/EC	
	Makita	EM2654LHC	Petrol String Trimmer		4,1/3,9	1,0/2,0	ISO22867			95 6	110 4	2,2/0,8	Uncertainty: K _{PN} /K _{WA}	ISO22868	
	Makita	EM2654LHC	Petrol String Trimmer		-	-	-			-	110 4	-	Guaranteed:111dB	2000/14/EC	
	Makita	EM2654LHN	Petrol String Trimmer		4,5/3,3	1,4/1,1	ISO22867			95 9	111 1	2,2/1,3	Uncertainty: K _{PN} /K _{WA}	ISO22868	
	Makita	EM2654LHN	Petrol String Trimmer		-	-	-			-	111 1	-	Guaranteed:112dB	2000/14/EC	
	Makita	EM2901LH	Petrol Brushcutter		4,4/4,5	0,9/1,6	ISO22867			95,5	105,4	2,3/2,2	Uncertainty: K _{PN} /K _{WA}	ISO22868	
	Makita	EM2901LH	Petrol Brushcutter		-	-	-			-	105,4	-	Guaranteed:108dB	2000/14/EC	
	Makita	EM2901LH	Petrol Brushcutter		4,3/3,9	1,2/1,8	ISO22867			94,9	108,2	1,4/1,6	Uncertainty: K _{PN} /K _{WA}	ISO22868	
	Makita	EM2901LH	Petrol Brushcutter		-	-	-			-	108,2	-	Guaranteed:110dB	2000/14/EC	

	Makita	EM2901LHN	Petrol String Trimmer		4,6/3,8	1,1/1,9	ISO22867				91,9	106,3	1,0/0,6	Uncertainty : K_{PM}/K_{WA}	ISO22868	
	Makita	EM2901LHN	Petrol String Trimmer		-	-	-				-	106,3	-	Guaranteed:107dB	2000/14/EC	
	Makita	EM2901UH	Petrol Brushcutter		3,0/3,6	1,0/1,0	ISO22867				95,5	105,4	2,3/2,2	Uncertainty : K_{PM}/K_{WA}	ISO22868	
	Makita	EM2901UH	Petrol Brushcutter		-	-	-				-	105,4	-	Guaranteed:108dB	2000/14/EC	
	Makita	EM2901UH	Petrol Brushcutter		2,6/3,9	1,0/1,1	ISO22867				94,9	108,2	1,4/1,6	Uncertainty : K_{PM}/K_{WA}	ISO22868	
	Makita	EM2901UH	Petrol Brushcutter		-	-	-				-	108,2	-	Guaranteed:110dB	2000/14/EC	
	Makita	EM2902LHN	Petrol String Trimmer		5,5/4,6	1,1/1,4	ISO22867				97,0	104,5	0,3/0,3	Uncertainty : K_{PM}/K_{WA}	ISO22868	
	Makita	EM2902LHN	Petrol String Trimmer		-	-	-				-	104,5	-	Guaranteed:105dB	2000/14/EC	
	Makita	EM3400L	Petrol Brushcutter		-	-	-				-	105 9	-	Guaranteed:107dB	2000/14/EC	
	Makita	EM3400L	Petrol Brushcutter		-	-	-				-	110 4	-	Guaranteed:112dB	2000/14/EC	
	Makita	EM3400U	Petrol Brushcutter		-	-	-				-	105 8	-	Guaranteed:106dB	2000/14/EC	
	Makita	EM3400U	Petrol Brushcutter		-	-	-				-	109 1	-	Guaranteed:110dB	2000/14/EC	
	Makita	EM4350L	Petrol Brushcutter		4,2/3,8	1,1/1,0	ISO22867				92,8	106,4	1,6/1,5	Uncertainty : K_{PM}/K_{WA}	ISO22868	
	Makita	EM4350L	Petrol Brushcutter				-				-	106,4	-	Guaranteed:108dB	2000/14/EC	
	Makita	EM4350L	Petrol Brushcutter		2,6/3,7	0,7/1,4	ISO22867				94,9	110,7	2,1/1,2	Uncertainty : K_{PM}/K_{WA}	ISO22868	
	Makita	EM4350L	Petrol Brushcutter				-				-	110,7	-	Guaranteed:112dB	2000/14/EC	
	Makita	EM4350RH	Petrol Brushcutter		3,4/2,4	1,0/0,7	ISO22867				92 5	110 6	1,7/0,7	Uncertainty : K_{PM}/K_{WA}	ISO22868	
	Makita	EM4350RH	Petrol Brushcutter		-	-	-				-	110 6	-	Guaranteed:111dB	2000/14/EC	
	Makita	EM4350RH	Petrol Brushcutter		3,2/2,7	1,7/0,8	ISO22867				83 5	104 1	1,1/1,1	Uncertainty : K_{PM}/K_{WA}	ISO22868	
	Makita	EM4350RH	Petrol Brushcutter		-	-	-				-	104 1	-	Guaranteed:105dB	2000/14/EC	
	Makita	EM4350U	Petrol Brushcutter		3,1/4,8	0,5/2,9	ISO22867				91,2	106,0	2,2/1,1	Uncertainty : K_{PM}/K_{WA}	ISO22868	
	Makita	EM4350U	Petrol Brushcutter				-				-	106,0	-	Guaranteed:107dB	2000/14/EC	
	Makita	EM4350U	Petrol Brushcutter		4,0/5,0	0,7/0,6	ISO22867				99,1	113,8	1,3/1,1	Uncertainty : K_{PM}/K_{WA}	ISO22868	
	Makita	EM4350U	Petrol Brushcutter				-					113,8	-	Guaranteed:115dB	2000/14/EC	
	Makita	EM4350U	Petrol Brushcutter		4,3/3,1	1,0/0,5	ISO22867									
	Makita	EM4350U	Petrol Brushcutter		-	-	-									
	Makita	EM4350U	Petrol Brushcutter		5,9/4,3	1,4/1,6	ISO22867									
	Makita	EM4350U	Petrol Brushcutter		-	-	-									
	Makita	EM4351U	Petrol Brushcutter		2,2/1,7	0,5/0,5	ISO22867				92,4	104,8	1,8/1,8	Uncertainty : K_{PM}/K_{WA}	ISO22868	
	Makita	EM4351U	Petrol Brushcutter				-				-	104,8	-	Guaranteed:107dB	2000/14/EC	
	Makita	EM4351U	Petrol Brushcutter		2,5/2,6	0,3/1,3	ISO22867				99,8	114,3	1,0/1,5	Uncertainty : K_{PM}/K_{WA}	ISO22868	
	Makita	EM4351U	Petrol Brushcutter				-				-	114,3	-	Guaranteed:116dB	2000/14/EC	
	Makita	EN4950H	Petrol Pole Hedge Trimmer		6,4/8,5	2,6/1,3	EN ISO 10517(ISO22867)				90	103,0	1,8/1,0	Uncertainty : K_{PM}/K_{WA}	EN ISO 10517(ISO22868)	
	Makita	EN4950H	Petrol Pole Hedge Trimmer		-	-	-				-	102 2	1,6	Guaranteed:104-dB	2000/14/EC	
	Makita	EN4951S	Petrol Pole Hedge Trimmer		5,1/7,0	1,5/3,1	EN ISO 10517(ISO22867)				90,2	104,1	1,0/0,4	Uncertainty : K_{PM}/K_{WA}	EN ISO 10517(ISO22868)	
	Makita	EN4951S	Petrol Pole Hedge Trimmer		-	-	-				-	102,2	0,6	Guaranteed:103dB	2000/14/EC	
	Makita	EN5950S	Petrol Pole Hedge Trimmer		6,6/9,8	0,3/2,1	EN ISO 10517(ISO22867)				87,1	102,8	2,9/1,8	Uncertainty : K_{PM}/K_{WA}	EN ISO 10517(ISO22868)	
	Makita	EN5950S	Petrol Pole Hedge Trimmer		-	-	-				-	99,6	1,9	Guaranteed:102-dB	2000/14/EC	
	Makita	EN7350S	Petrol Pole Hedge Trimmer		6,2/10,3	2,1/1,8	EN ISO 10517(ISO22867)				88,0	103,4	1,7/3,6	Uncertainty : K_{PM}/K_{WA}	EN ISO 10517(ISO22868)	
	Makita	EN7350S	Petrol Pole Hedge Trimmer		-	-	-				-	101,0	2,8	Guaranteed:104-dB	2000/14/EC	
	Makita	ER2550LH	Petrol String Trimmer		5,3/5,4	0,9/1,0	ISO22867				93,3	102,5	2,8/1,7	Uncertainty : K_{PM}/K_{WA}	ISO22868	
	Makita	ER2550LH	Petrol String Trimmer		-	-	-				-	105,5	-	Guaranteed:107dB	2000/14/EC	
	Makita	ER2600L	Petrol String Trimmer		3,9/5,1	1,5/1,5	ISO22867				91 3	111 3	0,9/0,9	Uncertainty : K_{PM}/K_{WA}	ISO22868	
	Makita	ER2600L	Petrol String Trimmer		-	-	-				-	111 3	-	Guaranteed:112dB	2000/14/EC	
	Makita	ER2650LH	Petrol String Trimmer		5,0/8,2	1,7/0,9	ISO22867				97,5	107,3	1,8/2,5	Uncertainty : K_{PM}/K_{WA}	ISO22868	
	Makita	ER2650LH	Petrol String Trimmer		-	-	-				-	107,3	-	Guaranteed:-110-dB	2000/14/EC	
	Makita	ETR2500	Edging Trimmer		12,4	0,9	ISO11789				95,6	105,6	2,4/2,5	Uncertainty : K_{PM}/K_{WA}	ISO11789	
	Makita	EX2650LH attached	Power Brush Attachment BR400MP		3,6/9,2	1,0/0,7	ISO22867				89,9	103,2	0,9/0,6	Uncertainty : K_{PM}/K_{WA}	ISO22868	
	Makita	EX2650LH attached	Power Brush Attachment BR400MP		-	-	-				-	103,9	-	Guaranteed:-104-dB	2000/14/EC (ISO22868)	
	Makita	EX2650LH attached	Edger Attachment EE400MP		3,5/8,6	1,6/1,7	ISO22867				89,5	99,7	2/2,6	Uncertainty : K_{PA}/K_{WA}	ISO22868	
	Makita	EX2650LH attached	Edger Attachment EE400MP		-	-	-				-	99,7	-	Guaranteed:-103-dB	2000/14/EC	
	Makita	EX2650LH attached	Brushcutter Attachment EM400MP		5,9/6,5	1,8/1,2	ISO22867				95,0	105,5	4,4/3,3	Uncertainty : K_{PM}/K_{WA}	ISO22868	
	Makita	EX2650LH attached	Brushcutter Attachment EM400MP		-	-	-				-	108,5	-	Guaranteed:-113-dB	2000/14/EC	
	Makita	EX2650LH attached	Brushcutter Attachment EM401MP		4,8/5,6	1,0/2,1	ISO22867				89,9	99,7	3,6/2,7	Uncertainty : K_{PM}/K_{WA}	ISO22868	

	Makita	EX2650LH attached	Brushcutter Attachment EM401MP		-	-	-			-	102,7	-	Guaranteed: -105-dB	2000/14/EC	
	Makita	EX2650LH attached	Brushcutter Attachment EM404MP		5,5/6,4	1,4/0,7	ISO22867			90,5	104,8	0,3/1,0	Uncertainty: K_{PN}/K_{WA}	ISO22868	
	Makita	EX2650LH attached	Brushcutter Attachment EM404MP		-	-	-			-	104,8	-	Guaranteed: -106-dB	2000/14/EC	
	Makita	EX2650LH attached	Brushcutter Attachment EM406MP		4,9/5,6	1,2/1,4	ISO22867			91,1	105,0	1,2/0,5	Uncertainty: K_{PN}/K_{WA}	ISO22868	
	Makita	EX2650LH attached	Brushcutter Attachment EM406MP		-	-	-			-	105,0	-	Guaranteed: -106-dB	2000/14/EC	
	Makita	EX2650LH attached	Brushcutter Attachment EM407MP		5,0/5,2	1,2/0,9	ISO22867(ISO11806-1)			89,5	104,7	1,4/2,7	Uncertainty: K_{PN}/K_{WA}	ISO22868(ISO11806-1)	
	Makita	EX2650LH attached	Brushcutter Attachment EM407MP		-	-	-			-	104,7	2,7	Guaranteed: -107-dB	2000/14/EC	
	Makita	EX2650LH attached	Brushcutter Attachment EM408MP		5,2/5,9	1,4/1,5	ISO22867(ISO11806-1)			89,2	103,6	3,7/1,0	Uncertainty: K_{PN}/K_{WA}	ISO22868(ISO11806-1)	*head 96-M10L(12
	Makita	EX2650LH attached	Brushcutter Attachment EM408MP		-	-	-			-	103,6	-	Guaranteed: -105-dB	2000/14/EC	
	Makita	EX2650LH attached	Brushcutter Attachment EM409MP		6,8/7,5	1,4/2,9	ISO22867(ISO11806-1)			89,2	103,3	3,1/1,6	Uncertainty: K_{PN}/K_{WA}	ISO22868(ISO11806-1)	*head 96-M10L(12
	Makita	EX2650LH attached	Brushcutter Attachment EM409MP		-	-	-			-	103,3	-	Guaranteed: -105-dB	2000/14/EC	
	Makita	EX2650LH attached	String Trimmer Attachment ER400MP		5,5/7,1	2,7/2,8	ISO22867			97,9	106,2	4,2/4,0	Uncertainty: K_{PN}/K_{WA}	ISO22868	
	Makita	EX2650LH attached	String Trimmer Attachment ER400MP		-	-	-			-	109,2	-	Guaranteed: -116-dB	2000/14/EC	
	Makita	EX2650LH attached	Pole Saw Attachment EY400MP		4,2/9,4	2,0/2,0	ISO22867			93,0	104,5	2,5/2,5	Uncertainty: K_{PN}/K_{WA}	ISO22868	
	Makita	EX2650LH attached	Pole Saw Attachment EY400MP + LE400MP		3,4/4,8	2,0/2,0	ISO22867			90,3	107,8	2,5/2,5	Uncertainty: K_{PN}/K_{WA}	ISO22868	
	Makita	EX2650LH attached	Pole Saw Attachment EY401MP		3,8/6,5	2,0/2,0	ISO22867			92,6	104,7	2,5/2,5	Uncertainty: K_{PN}/K_{WA}	ISO22868	
	Makita	EX2650LH attached	Pole Saw Attachment EY401MP + LE400MP		3,4/5,6	2,0/2,0	ISO22867			90,5	107,9	2,5/2,5	Uncertainty: K_{PN}/K_{WA}	ISO22868	
	Makita	EX2650LH attached	Pole Saw Attachment EY402MP		4,0 6,4	1,5	ISO22867(ISO11806-1)			91	106	3	Uncertainty: K_{PN}/K_{WA}	ISO22868(ISO11806-1)	
	Makita	EX2650LH attached	Pole Saw Attachment EY402MP		4,4 6,8	1,5	ISO22867(ISO11806-1)			93	107	3	Uncertainty: K_{PN}/K_{WA}	ISO22868(ISO11806-1)	
	Makita	EX2650LH attached	Pole Saw Attachment EY403MP		3,8 7,1	1,5	ISO22867(ISO11806-1)			93	107	3	Uncertainty: K_{PN}/K_{WA}	ISO22868(ISO11806-1)	
	Makita	EX2650LH attached	Pole Saw Attachment EY403MP		4,0 7,1	1,5	ISO22867(ISO11806-1)			92	107	3	Uncertainty: K_{PN}/K_{WA}	ISO22868(ISO11806-1)	
	Makita	EX2650LH attached	Pole Saw Attachment EY402MP + LE400MP		5,2 9,0	1,5	ISO22867(ISO11806-1)			91	106	3	Uncertainty: K_{PN}/K_{WA}	ISO22868(ISO11806-1)	without LE400MP
	Makita	EX2650LH attached	Pole Saw Attachment EY402MP + LE400MP		4,7 9,3	1,5	ISO22867(ISO11806-1)			93	107	3	Uncertainty: K_{PN}/K_{WA}	ISO22868(ISO11806-1)	without LE400MP
	Makita	EX2650LH attached	Pole Saw Attachment EY403MP + LE400MP		4,5 9,5	1,5	ISO22867(ISO11806-1)			93	107	3	Uncertainty: K_{PN}/K_{WA}	ISO22868(ISO11806-1)	without LE400MP
	Makita	EX2650LH attached	Pole Saw Attachment EY403MP + LE400MP		4,8 9,3	1,5	ISO22867(ISO11806-1)			92	107	3	Uncertainty: K_{PN}/K_{WA}	ISO22868(ISO11806-1)	without LE400MP
	Makita	EX2650LH attached	Hedge Trimmer Attachment EN400MP		5,0/8,4	0,7/1,8	ISO10517			93,1	102,9	4,4/4,8	Uncertainty: K_{PN}/K_{WA}	ISO10517	
	Makita	EX2650LH attached	Hedge Trimmer Attachment EN400MP		-	-	-			-	103,8	-	Guaranteed: -109-dB	2000/14/EC	
	Makita	EX2650LH attached	Hedge Trimmer Attachment EN400MP + LE400MP		4,3/8,0	0,7/1,7	ISO10517			87,8	103,0	1,9/2,0	Uncertainty: K_{PN}/K_{WA}	ISO22868	
	Makita	EX2650LH attached	Hedge Trimmer Attachment EN400MP + LE400MP		-	-	-			-	104,0	-	Guaranteed: -106-dB	2000/14/EC	
	Makita	EX2650LH attached	Pole Hedge Trimmer Attachment EN401MP		5,9/7,7	2,5/0,8	EN ISO 10517(ISO22867)			90,7	104,3	1,6/3,8	Uncertainty: K_{PN}/K_{WA}	EN ISO 10517(ISO22868)	
	Makita	EX2650LH attached	Pole Hedge Trimmer Attachment EN401MP		-	-	-			-	102,1	1,7	Guaranteed: -104-dB	2000/14/EC	
	Makita	EX2650LH attached	Pole Hedge Trimmer Attachment EN401MP + LE400MP		7,6/9,6	2,7/2,2	EN ISO 10517(ISO22867)			89,2	103,7	2,9/2,2	Uncertainty: K_{PN}/K_{WA}	EN ISO 10517(ISO22868)	
	Makita	EX2650LH attached	Pole Hedge Trimmer Attachment								102,0	1,6	Guaranteed: -104-dB	2000/14/EC	
	Makita	EX2650LH attached	Pole Hedge Trimmer Attachment		6,6/7,8	3,6/2,0	EN ISO 10517(ISO22867)			87,8	102,9	0,8/1,6	Uncertainty: K_{PN}/K_{WA}	EN ISO 10517(ISO22868)	
	Makita	EX2650LH attached	Pole Hedge Trimmer Attachment								102,3	1,7	Guaranteed: -104-dB	2000/14/EC	
	Makita	EX2650LH attached	Pole Hedge Trimmer Attachment		9,2/10,8	2,0/1,4	EN ISO 10517(ISO22867)			88,7	103,6	1,1/0,7	Uncertainty: K_{PN}/K_{WA}	EN ISO 10517(ISO22868)	
	Makita	EX2650LH attached	Pole Hedge Trimmer Attachment								102,9	0,9	Guaranteed: -104-dB	2000/14/EC	
	Makita	EX2650LH attached	Ground Trimmer Attachment		6,3/9,1	4,0/1,7	EN ISO 10517(ISO22867)			88,7	103,8	1,0/2,0	Uncertainty: K_{PN}/K_{WA}	EN ISO 10517(ISO22868)	
	Makita	EX2650LH attached	Ground Trimmer Attachment								101,3	0,7	Guaranteed: -102dB	2000/14/EC	
	Makita	EX2650LH attached	Cultivator Attachment		4,4/5,0	2,3/1,1	ISO22867			93,7	99,7	2,6/1,2	Uncertainty: K_{PN}/K_{WA}	ISO22868	
	Makita	EX2650LH attached	Coffee Harvester Attachment		5,3/4,2	0,9/0,3	ISO22867			87,9	102,5	0,2/0,3	Uncertainty: K_{PN}/K_{WA}	ISO22868	
	Makita	EX2650LH attached	Coffee Harvester Attachment		4,9/7,1	1,5/1,5	ISO22867			99,8	99,8	2,3/1,1	Uncertainty: K_{PN}/K_{WA}	ISO22868	
	Makita	EX2650LH attached	Coffee Harvester Attachment		4,0/6,4	0,7/0,6	ISO22867			88,1	100,8	2,2/2,3	Uncertainty: K_{PN}/K_{WA}	ISO22868	
	Makita	EX2650LH attached	Power Sweep Attachment		4,1/8,3	1,5/1,4	ISO22867			88,6	102,9	1,8/0,7	Uncertainty: K_{PN}/K_{WA}	ISO22868	
	Makita	EX2650LH attached	Power Sweep Attachment								103,6		Guaranteed: -104-dB	2000/14/EC	
	Makita	EX2650LH attached	Blower Attachment		3,3/6,5	0,4/0,8	ISO22867(EN15503)			93,3	105,6	0,6/0,4	Uncertainty: K_{PN}/K_{WA}	ISO22868(EN15503)	
	Makita	EX2650LH attached	Blower Attachment								102,9	0,5	Guaranteed: -103-dB	2000/14/EC	
	Makita	EX2650LH attached	Blower Attachment		5,4/6,7	1,1/1,9	ISO22867(EN15503)			92,4	104,0	1,2/0,5	Uncertainty: K_{PN}/K_{WA}	ISO22868(EN15503)	
	Makita	EX2650LH attached	Blower Attachment								102,3	0,3	Guaranteed: -103-dB	2000/14/EC	
	Makita	EX2650H	Telescopic Petrol pole saw		7,2/5,3	2,0/2,0	ISO22867			89,5	107,3	2,5/2,5	Uncertainty: K_{PA}/K_{WA}	ISO22868	
	Makita	EX2650H	Telescopic Petrol pole saw		8,6/6,1	2,0/2,0	ISO22867				107,3		Guaranteed: -110-dB	2000/14/EC	
	Makita	FL061FD	Angle Screwdriver	10/10	2,5	1,5	60745-2-2	10/10	70			3	no-load	60745-2-2	
	Makita	FL062FD	Angle Screwdriver	10/10	2,5	1,5	60745-2-2	10/10	70			3	no-load	60745-2-2	
	Makita	FL001G	Cordless Pin Nailer	10/10	2,5	1,5	60745-2-16	10/10	81	92	3		Nailing wood	60745-2-16	
	Makita	FS2200	Screwdriver	10/10	2,5	1,5	60745-2-2	10/10	83	94	3		no-load	60745-2-2	
	Makita	FS2300	Screwdriver	10/10	0,8	1,5	EN6284-2-2	86		94	3		no-load	EN6284-2-2	
	Makita	FS2300X	Screwdriver	10/10	0,8	1,5	EN6284-2-2	86		94	3		no-load	EN6284-2-2	
	Makita	FS2700	Screwdriver	10/10	0,8	1,5	EN6284-2-2	86		94	3		no-load	EN6284-2-2	
	Makita	FS2701	Screwdriver	10/10	0,8	1,5	EN6284-2-2	86		94	3		no-load	EN6284-2-2	
	Makita	FS4000	Screwdriver	10/10	0,8	1,5	EN6284-2-2	86		93	3		no-load	EN6284-2-2	
	Makita	FS4000 X	Screwdriver	10/10	0,8	1,5	EN6284-2-2	86		93	3		no-load	EN6284-2-2	
	Makita	FS4200	Screwdriver	10/10	0,4	1,5	EN6284-2-2	86		93	3		no-load	EN6284-2-2	
	Makita	FS4300	Screwdriver	10/10	0,4	1,5	EN6284-2-2	86		93	3		no-load	EN6284-2-2	
	Makita	FS4300X	Screwdriver	10/10	0,5	1,5	EN6284-2-2	86		93	3		no-load	EN6284-2-2	
	Makita	FS6300(FS6200)	Screwdriver	10/10	0,5	1,5	EN6284-2-2	86		93	3		no-load	EN6284-2-2	
	Makita	FS6300R	Screwdriver	10/10	0,5	1,5	EN6284-2-2	86		93	3		no-load	EN6284-2-2	
	Makita	FS6300X	Screwdriver	10/10	0,5	1,5	EN6284-2-2	86		93	3		no-load	EN6284-2-2	
	Makita	FT022FD	Screwdriver	10/10	2,5	1,5	60745-2-2	10/10	70			3	no-load	60745-2-2	
	Makita	FT044FD	Screwdriver	10/10	2,5	1,5	60745-2-2	10/10	70			3	no-load	60745-2-2	
	Makita	FT084FD	Screwdriver	10/10	2,5	1,5	60745-2-2	10/10	70			3	no-load	60745-2-2	
	Makita	FT126FD	Screwdriver	10/10	2,5	1,5	60745-2-2	10/10	70			3	no-load	60745-2-2	
	Makita	GA003G GA006G	Angle Grinder	10/10	5,0	1,5	62841-2-3	84		92	3		Lp:Result converted to 0.7m p	62841-2-3	Normal side grip
	Makita	GA003G GA006G	Angle Grinder	10/10	2,5	1,5	62841-2-3							62841-2-3	Normal side grip
	Makita	GA003G GA006G	Angle Grinder	10/10	5,5	1,5	62841-2-3	84		92	3		Lp:Result converted to 0.7m p	62841-2-3	Anti vib side grip
	Makita	GA003G GA006G	Angle Grinder	10/10	2,5	1,5	62841-2-3							62841-2-3	Anti vib side grip
	Makita	GA004G GA007G	Angle Grinder	10/10	5,5	1,5	62841-2-3	84		92	3		Lp:Result converted to 0.7m p	62841-2-3	Normal side grip

	Makita	UC006G	Cordless Chain Saw		2,8	1,5	EN62841-1and EN ISO 11681-2 as applicable		91	-	99	3	Chain:25AP Guide bar:Carving	EN62841-1and EN ISO 11681-2 as applicable	
	Makita	UC006G	Cordless Chain Saw		-	-	-			-	102,4	2,7	Guaranteed:-105-dB	2000/14/EC (ISO9207)	ar:CarvingUnified
	Makita	UC013G(UC010G, UC015	Cordless Chain Saw		3,1	1,5	EN62841-4-1		92	-	100	3	Chain:80TXL Guide bar:Sprocket nose	EN62841-4-1	
	Makita	UC013G(UC010G, UC015	Cordless Chain Saw		-	-	-			-	101,1	1,7	Guaranteed:-103-dB	2000/14/EC (ISO9207)	XLGuide bar:Sprock
	Makita	UC013G(UC010G, UC015	Cordless Chain Saw		4,4	1,5	EN62841-4-1		94	-	102	3	Chain:91PX Guide bar:Sprocket nose	EN62841-4-1	
	Makita	UC013G(UC010G, UC015	Cordless Chain Saw		-	-	-			-	102,0	2,3	Guaranteed:-104-dB	2000/14/EC (ISO9207)	XGuide bar:Sprock
	Makita	UC017G(UC014G, UC015	Cordless Chain Saw		3,0	1,5	EN62841-4-1		92	-	100	3	Chain:80TXL Guide bar:Sprocket nose	EN62841-4-1	
	Makita	UC017G(UC014G, UC015	Cordless Chain Saw		-	-	-			-	101,1	1,7	Guaranteed:-103-dB	2000/14/EC (ISO9207)	XLGuide bar:Sprock
	Makita	UC017G(UC014G, UC015	Cordless Chain Saw		5,0	1,5	EN62841-4-1		94	-	102	3	Chain:91PX Guide bar:Sprocket nose	EN62841-4-1	
	Makita	UC017G(UC014G, UC015	Cordless Chain Saw		-	-	-			-	102,0	2,3	Guaranteed:-104-dB	2000/14/EC (ISO9207)	XGuide bar:Sprock
	Makita	UC023G(UC022G UC021	Cordless Chain Saw		3,5	1,5	EN62841-4-1		93	-	101	3	Chain:80TXL Guide bar:Sprocket nose	EN62841-4-1	
	Makita	UC023G(UC022G UC021	Cordless Chain Saw		-	-	-			-	100,3	1,8	Guaranteed:-102-dB	2000/14/EC (ISO9207)	XLGuide bar:Sprock
	Makita	UC026G(UC025G UC024	Cordless Chain Saw		3,5	1,5	EN62841-4-1		93	-	101	3	Chain:80TXL Guide bar:Sprocket nose	EN62841-4-1	
	Makita	UC026G(UC025G UC024	Cordless Chain Saw		-	-	-			-	100,3	1,8	Guaranteed:-102-dB	2000/14/EC (ISO9207)	XLGuide bar:Sprock
	Makita	UC029G	Cordless Pruning Saw		4,6	1,5	EN62841-4-1		81	-	89	3	Chain:80TXL Guide bar:150mm (no Sprocket)	EN62841-4-1	uide bar:150mm (r
	Makita	UC029G	Cordless Pruning Saw		-	-	-			-	89	2,4	Guaranteed:-92-dB	2000/14/EC+2024/1208/EU	uide bar:150mm (r
Added	Makita	UC030G	Cordless Chain Saw		4,1	1,5	EN62841-4-1		96	-	104	3	Chain:22BPX Guide bar:500mm Sprocket nose	EN62841-4-1	
Added	Makita	UC030G	Cordless Chain Saw		-	-	-			-	104	2,4	Guaranteed:-106-dB	2000/14/EC+2024/1208/EU (EN62841-4-1)	uide bar:500mm S
Added	Makita	UC030G	Cordless Chain Saw		5,3	1,5	EN62841-4-1		99	-	107	3	Chain:Rescue Guide bar:500mm Sprocket nose	EN62841-4-1	
Added	Makita	UC030G	Cordless Chain Saw		-	-	-			-	107	2,4	Guaranteed:-109-dB	2000/14/EC+2024/1208/EU (EN62841-4-1)	uide bar:500mm S
Added	Makita	UC031G	Cordless Chain Saw		3,1	1,5	EN62841-4-1			97	105	3	Chain:90PX Guide bar:300mm Sprocket nose	EN62841-4-1	
Added	Makita	UC031G	Cordless Chain Saw		-	-	-			-	100	2,4	Guaranteed:-102-dB	2000/14/EC+2024/1208/EU (EN62841-4-1)	uide bar:300mm S
Added	Makita	UC031G	Cordless Chain Saw		-	-	-			-	102	2,4	Guaranteed:-104-dB	2000/14/EC+2024/1208/EU (EN62841-4-1)	uide bar:300mm S
	Makita	UC100D	Cordless Pruning Saw		4,8	1,5	EN62841-4-1		79	-	87	3	Chain:80TXL Guide bar:100mm (no Sprocket)	EN62841-4-1	
	Makita	UC100D	Cordless Pruning Saw		-	-	-			-	93,4	2,0	Guaranteed:-95-dB	2000/14/EC (ISO9207)	uide bar:100mm (r
	Makita	UC120D	Cordless Chain Saw		8,9	2,6	60745-2-13			80	-	3,38	-	60745-2-13	
	Makita	UC120D	Cordless Chain Saw		-	-	-			-	90	-	Guaranteed:-94-dB	2000/14/EC	
	Makita	UC3020A	Chain Saw		2,8(F) 4,6(R)	1,5	60745-2-13			89	100	1	-	60745-2-13	
	Makita	UC3020A	Chain Saw		-	-	-			-	100	-	Guaranteed:-101-dB	2000/14/EC	
	Makita	UC3030A	Chain Saw		4,7(F) 5,6(R)	1,5	60745-2-13			90,8	101,8	0,73	-	60745-2-13	
	Makita	UC3030A	Chain Saw		-	-	-			-	101,8	-	Guaranteed:-103-dB	2000/14/EC	
	Makita	UC3041A	Chain Saw		5,3	1,5	EN62841-4-1		92	-	100	3	Chain:90PX Guide bar:400mm Sprocket nose	EN62841-4-1	
	Makita	UC3041A	Chain Saw		-	-	-			-	102,2	-	Guaranteed:-104-dB	2000/14/EC	
	Makita	UC3050A	Chain Saw		6,7	1,5	EN62841-4-1		92	-	100	3	Chain:91PX Guide bar:450mm Sprocket nose	EN62841-4-1	
	Makita	UC3050A	Chain Saw		-	-	-			-	101,9	-	Guaranteed:-103-dB	2000/14/EC	
	Makita	UC3051A	Chain Saw		6,7	1,5	EN62841-4-1		92	-	100	3	Chain:91PX Guide bar:450mm Sprocket nose	EN62841-4-1	
	Makita	UC3051A	Chain Saw		-	-	-			-	101,9	-	Guaranteed:-103-dB	2000/14/EC	
	Makita	UC3520A	Chain Saw		2,8(F) 4,6(R)	1,5	60745-2-13			89	100	1	-	60745-2-13	
	Makita	UC3520A	Chain Saw		-	-	-			-	100	-	Guaranteed:-101-dB	2000/14/EC	
	Makita	UC3530A	Chain Saw		4,7(F) 5,6(R)	1,5	60745-2-13			90,8	101,8	0,73	-	60745-2-13	
	Makita	UC3530A	Chain Saw		-	-	-			-	101,8	-	Guaranteed:-103-dB	2000/14/EC	
	Makita	UC3541A	Chain Saw		5,3	1,5	EN62841-4-1		92	-	100	3	Chain:90PX Guide bar:400mm Sprocket nose	EN62841-4-1	
	Makita	UC3541A	Chain Saw		-	-	-			-	102,2	-	Guaranteed:-104-dB	2000/14/EC	
	Makita	UC3550A	Chain Saw		6,7	1,5	EN62841-4-1		92	-	100	3	Chain:91PX Guide bar:450mm Sprocket nose	EN62841-4-1	
	Makita	UC3550A	Chain Saw		-	-	-			-	101,9	-	Guaranteed:-103-dB	2000/14/EC	
	Makita	UC3550AP	Chain Saw		6,7	1,5	EN62841-4-1		92	-	100	3	Chain:91PX Guide bar:450mm Sprocket nose	EN62841-4-1	
	Makita	UC3550AP	Chain Saw		-	-	-			-	101,9	-	Guaranteed:-103-dB	2000/14/EC	
	Makita	UC3551A	Chain Saw		6,7	1,5	EN62841-4-1		92	-	100	3	Chain:91PX Guide bar:450mm Sprocket nose	EN62841-4-1	
	Makita	UC3551A	Chain Saw		-	-	-			-	101,9	-	Guaranteed:-103-dB	2000/14/EC	
	Makita	UC4020A	Chain Saw		2,8(F) 4,6(R)	1,5	60745-2-13			89	100	1	-	60745-2-13	
	Makita	UC4020A	Chain Saw		-	-	-			-	100	-	Guaranteed:-101-dB	2000/14/EC	
	Makita	UC4030A	Chain Saw		4,7(F) 5,6(R)	1,5	60745-2-13			90,8	101,8	0,73	-	60745-2-13	
	Makita	UC4030A	Chain Saw		-	-	-			-	101,8	-	Guaranteed:-103-dB	2000/14/EC	
	Makita	UC4041A	Chain Saw		5,3	1,5	EN62841-4-1		92	-	100	3	Chain:90PX Guide bar:400mm Sprocket nose	EN62841-4-1	
	Makita	UC4041A	Chain Saw		-	-	-			-	102,2	-	Guaranteed:-104-dB	2000/14/EC	

	Makita	UX01G	String Trimmer Attachment EM406MP		-	-	-			-	87,8	1,0	Guaranteed -89-dB	2000/14/EC	
	Makita	UX01G	Brushcutter Attachment EM407MP	≤	2,5	1,5	ISO22867(ISO11806-1)			84,7	99,0	1,7/1,3	Uncertainty: K _{PA} /K _{WA}	ISO22868(ISO11806-1)	
	Makita	UX01G	Brushcutter Attachment EM407MP		-	-	-			-	99,0	1,3	Guaranteed -100-dB	2000/14/EC	
	Makita	UX01G	String Trimmer Attachment EM408MP	≤	2,5	1,5	ISO22867(ISO11806-1)			80,7	94,7	1,7/3,0	Uncertainty: K _{PA} /K _{WA}	ISO22868(ISO11806-1)	230mm Blade 4
	Makita	UX01G	String Trimmer Attachment EM408MP		-	-	-			-	94,7	3,0	Guaranteed -98-dB	2000/14/EC	
	Makita	UX01G	String Trimmer Attachment EM408MP	≤	2,5	1,5	ISO22867(ISO11806-1)			79,5	92,8	1,3/2,7	Uncertainty: K _{PA} /K _{WA}	ISO22868(ISO11806-1)/EN50636-2-91	head 96-M10L(12
	Makita	UX01G	String Trimmer Attachment EM408MP		-	-	-			-	90,3	2,5	Guaranteed -93-dB	2000/14/EC	
	Makita	UX01G	String Trimmer Attachment EM408MP	≤	2,5	1,5	ISO22867(ISO11806-1)			80,5	92,2	1,1/2,8	Uncertainty: K _{PA} /K _{WA}	ISO22868(ISO11806-1)/EN50636-2-91	blade assembly(12
	Makita	UX01G	String Trimmer Attachment EM408MP		-	-	-			-	90,9	1,9	Guaranteed -93-dB	2000/14/EC	
	Makita	UX01G	String Trimmer Attachment EM409MP	≤	2,5	1,5	ISO22867(ISO11806-1)			80,6	93,4	1,2/2,3	Uncertainty: K _{PA} /K _{WA}	ISO22868(ISO11806-1)/EN50636-2-91	head 96-M10L(12
	Makita	UX01G	String Trimmer Attachment EM409MP		-	-	-			-	89,4	2,4	Guaranteed -92-dB	2000/14/EC	
	Makita	UX01G	String Trimmer Attachment EM409MP	≤	2,5	1,5	ISO22867(ISO11806-1)			81,0	91,9	1,4/2,4	Uncertainty: K _{PA} /K _{WA}	ISO22868(ISO11806-1)/EN50636-2-91	blade assembly(12
	Makita	UX01G	String Trimmer Attachment EM409MP		-	-	-			-	91,1	2,1	Guaranteed -94-dB	2000/14/EC	
	Makita	UX01G	Pole Hedge Trimmer Attachment EN401MP	≤	3,4 2,5	1,5	EN62841-4-2		-	85	-	3	Uncertainty: K _{PA}	EN62841-4-2	
	Makita	UX01G	Pole Hedge Trimmer Attachment EN401MP		-	-	-			-	95	1,1	Guaranteed -96-dB	EN62841-4-2	
	Makita	UX01G	Pole Hedge Trimmer Attachment EN401MP		-	-	-			-	94,9	1,1	Guaranteed -96-dB	2000/14/EC	
	Makita	UX01G	Pole Hedge Trimmer Attachment EN401MP + LE400MP		5,4 2,7	1,5	EN62841-4-2		-	82	-	3	Uncertainty: K _{PA}	EN62841-4-2	
	Makita	UX01G	Pole Hedge Trimmer Attachment EN401MP + LE400MP		-	-	-			-	96	1,4	Guaranteed -98-dB	EN62841-4-2	
	Makita	UX01G	Pole Hedge Trimmer Attachment EN401MP + LE400MP		-	-	-			-	96,2	1,4	Guaranteed -98-dB	2000/14/EC	
	Makita	UX01G	Pole Hedge Trimmer Attachment EN402MP	≤	2,5 2,5	1,5	EN62841-4-2		-	83	-	3	Uncertainty: K _{PA}	EN62841-4-2	
	Makita	UX01G	Pole Hedge Trimmer Attachment EN402MP		-	-	-			-	92	2,3	Guaranteed -95-dB	EN62841-4-2	
	Makita	UX01G	Pole Hedge Trimmer Attachment EN402MP		-	-	-			-	92,7	2,0	Guaranteed -95-dB	2000/14/EC	
	Makita	UX01G	Pole Hedge Trimmer Attachment EN402MP + LE400MP		5,0 3,4	1,5	EN62841-4-2		-	79	-	3	Uncertainty: K _{PA}	EN62841-4-2	
	Makita	UX01G	Pole Hedge Trimmer Attachment EN402MP + LE400MP		-	-	-			-	94	1,8	Guaranteed -96-dB	EN62841-4-2	
	Makita	UX01G	Pole Hedge Trimmer Attachment EN402MP + LE400MP		-	-	-			-	93,4	1,7	Guaranteed -95-dB	2000/14/EC	
	Makita	UX01G	Pole Hedge Trimmer Attachment EN410MP		6,7 3,1	1,5	EN62841-4-2		-	81	-	3	Uncertainty: K _{PA}	EN62841-4-2	
	Makita	UX01G	Pole Hedge Trimmer Attachment EN410MP		-	-	-			-	91	2,0	Guaranteed -93-dB	EN62841-4-2	
	Makita	UX01G	Pole Hedge Trimmer Attachment EN410MP		-	-	-			-	90,6	2,0	Guaranteed -93-dB	2000/14/EC	
	Makita	UX01G	Pole Hedge Trimmer Attachment EN410MP + LE400MP	≤	4,4 2,5	1,5	EN62841-4-2		-	80	-	3	Uncertainty: K _{PA}	EN62841-4-2	
	Makita	UX01G	Pole Hedge Trimmer Attachment EN410MP + LE400MP		-	-	-			-	91	1,7	Guaranteed -93-dB	EN62841-4-2	
	Makita	UX01G	Pole Hedge Trimmer Attachment EN410MP + LE400MP		-	-	-			-	91,1	1,7	Guaranteed -93-dB	2000/14/EC	
	Makita	UX01G	Ground Trimmer Attachment EN420MP	≤	2,9 2,5	1,5	EN62841-4-2		-	84	-	3	Uncertainty: K _{PA}	EN62841-4-2	
	Makita	UX01G	Ground Trimmer Attachment EN420MP		-	-	-			-	94	0,4	Guaranteed -94-dB	EN62841-4-2	
	Makita	UX01G	Ground Trimmer Attachment EN420MP		-	-	-			-	93,5	0,4	Guaranteed -94-dB	2000/14/EC	
	Makita	UX01G	Ground Trimmer Attachment EN421MP	≤	3,1 2,5	1,5	EN62841-4-2			81	92	3	Uncertainty: K _{PA} /K _{WA}	EN62841-4-2	
	Makita	UX01G	Ground Trimmer Attachment EN421MP		-	-	-			-	92,2	0,7	Guaranteed -93-dB	2000/14/EC	
	Makita	UX01G	Ground Trimmer Attachment EN422MP	≤	2,5 2,5	1,5	EN62841-4-2		-	81	-	3	Uncertainty: K _{PA}	EN62841-4-2	
	Makita	UX01G	Ground Trimmer Attachment EN422MP		-	-	-			-	92	1,9	Guaranteed -94-dB	EN62841-4-2	
	Makita	UX01G	Ground Trimmer Attachment EN422MP		-	-	-			-	91,6	2,0	Guaranteed -94-dB	2000/14/EC	
	Makita	UX01G	Ground Trimmer Attachment EN422MP + LE400MP		-	-	-			-	92,9	1,8	Guaranteed -95-dB	2000/14/EC	
	Makita	UX01G	Ground Trimmer Attachment EN424MP	≤	2,5	1,5	EN62841-1			80	88	3	Uncertainty: K _{PA} /K _{WA}	EN62841-1	
	Makita	UX01G	Ground Trimmer Attachment (lawnmower) EN424MP		-	-	-			-	88,1	0,9	Guaranteed -90-dB	2000/14/EC	
Added	Makita	UX01G	Ground Trimmer Attachment EN425MP	≤	2,5	1,5	EN62841-1			78	88	3	Uncertainty: K _{PA} /K _{WA}	EN62841-1	
	Makita	UX01G	Pole Saw Attachment EY401MP	≤	2,5	1,5	ISO22867(ISO11680-1)			94	103	3	Uncertainty: K _{PA} /K _{WA}	ISO22868(ISO11680-1)	r : 255mm / chain
	Makita	UX01G	Pole Saw Attachment EY401MP + LE400MP	≤	2,5	1,5	ISO22867(ISO11680-1)			85	103	3	Uncertainty: K _{PA} /K _{WA}	ISO22868(ISO11680-1)	r : 255mm / chain
	Makita	UX01G	Pole Saw Attachment EY402MP	≤	4,2 2,5	1,5	ISO22867(ISO11680-1)			94	104	3	Uncertainty: K _{PA} /K _{WA}	ISO22868(ISO11680-1)	
	Makita	UX01G	Pole Saw Attachment EY402MP	≤	2,5	1,5	ISO22867(ISO11680-1)			97	103	3	Uncertainty: K _{PA} /K _{WA}	ISO22868(ISO11680-1)	
	Makita	UX01G	Pole Saw Attachment EY403MP	≤	4,0 2,5	1,5	ISO22867(ISO11680-1)			95	102	3	Uncertainty: K _{PA} /K _{WA}	ISO22868(ISO11680-1)	
	Makita	UX01G	Pole Saw Attachment EY403MP	≤	4,7 2,5	1,5	ISO22867(ISO11680-1)			95	103	3	Uncertainty: K _{PA} /K _{WA}	ISO22868(ISO11680-1)	
	Makita	UX01G	Pole Saw Attachment EY402MP + LE400MP	≤	2,5	1,5	ISO22867(ISO11680-1)			94	104	3	Uncertainty: K _{PA} /K _{WA}	ISO22868(ISO11680-1)	without LE400MP
	Makita	UX01G	Pole Saw Attachment EY402MP + LE400MP	≤	2,5	1,5	ISO22867(ISO11680-1)			97	103	3	Uncertainty: K _{PA} /K _{WA}	ISO22868(ISO11680-1)	without LE400MP
	Makita	UX01G	Pole Saw Attachment EY403MP + LE400MP	≤	3,2 2,5	1,5	ISO22867(ISO11680-1)			95	102	3	Uncertainty: K _{PA} /K _{WA}	ISO22868(ISO11680-1)	without LE400MP
	Makita	UX01G	Pole Saw Attachment EY403MP + LE400MP	≤	3,5 2,5	1,5	ISO22867(ISO11680-1)			95	103	3	Uncertainty: K _{PA} /K _{WA}	ISO22868(ISO11680-1)	without LE400MP

	Makita	UX01G	Cultivator Attachment KR400MP	≤	2,5	1,5	EN709			77,8	86,6	0,7/1,2	Uncertainty: K _{PA} /K _{WA}	EN709		
	Makita	UX01G	Cultivator Attachment KR401MP	≤	2,5	1,5	EN709			77,7	86,7	0,3/2,0	Uncertainty: K _{PA} /K _{WA}	EN709		
	Makita	UX01G	Power Brush Attachment BR400MP	≤	2,5	1,5	EN60335-2-72			80,2	88,9	1,0/0,8	Uncertainty: K _{PA} /K _{WA}	EN60335-2-72	p at Operators ea	
	Makita	UX01G	Power Sweep Attachment SW400MP	≤	2,5	1,5	EN60335-2-72			80,3	88,3	0,2/0,6	Uncertainty: K _{PA} /K _{WA}	EN60335-2-72	p at Operators ea	
	Makita	UX01G	Pump Attachment PF400MP	≤	2,5	1,5	ISO22867			75	90	2,5	Uncertainty: K _{PA} /K _{WA}	ISO20361		
	Makita	UX01G	Pump Attachment PF400MP		-	-	-			-	90,7	2,5	Guaranteed -93-dB	2000/14/EC		
	Makita	UX01G	Snow Blower Attachment SN400MP	≤	2,5	1,5	ISO8437-4		-	81	-	3		ISO11201(ISO8437-4)		
	Makita	UX01G	Snow Blower Attachment SN400MP		-	-	-			-	91	1,9	Guaranteed -93-dB	ISO3744(ISO8437-4) 2000/14/EC		
	Makita	UX01G	Blower Attachment UB400MP	≤	4,6	1,5	EN50636-2-100			92,1	104,1	1,6/1,3	Uncertainty: K _{PA} /K _{WA}	EN50636-2-100		
	Makita	UX01G	Blower Attachment UB400MP		-	-	-			-	104,1	1,3	Guaranteed -105-dB	2000/14/EC		
	Makita	UX01G	Blower Attachment UB401MP	≤	2,5	1,7	EN50636-2-100			85,6	97,1	2,1/1,0	Uncertainty: K _{PA} /K _{WA}	EN50636-2-100		
	Makita	UX01G	Blower Attachment UB401MP		-	-	-			-	97,1	1,0	Guaranteed -98-dB	2000/14/EC		
	Makita	UX01G	Blower Attachment UB402MP	≤	2,5	1,5	EN50636-2-100			81,7	90,8	1,9/1,7	Uncertainty: K _{PA} /K _{WA}	EN50636-2-100		
	Makita	UX01G	Blower Attachment UB402MP		-	-	-			-	91,2	1,8	Guaranteed -93-dB	2000/14/EC		
	Makita	UX01G	Blower Attachment UB403MP	≤	2,5	1,5	EN IEC 62841-4-6		-	91	-	3	Uncertainty: K _{PA}	EN IEC 62841-4-6		
	Makita	UX01G	Blower Attachment UB403MP		-	-	-			-	100	2,1	Guaranteed -102-dB	EN IEC 62841-4-6		
	Makita	UX01G	Blower Attachment UB403MP		-	-	-			-	98,4	2,1	Guaranteed -100-dB	2000/14/EC+2024/1208/EU		
	Makita	UX01G	Blower Attachment UB403MP	≤	2,5	1,5	EN IEC 62841-4-6		-	100	-	3	Uncertainty: K _{PA}	EN IEC 62841-4-6		
	Makita	UX01G	Blower Attachment UB403MP		-	-	-			-	101	2,2	Guaranteed -103-dB	EN IEC 62841-4-6		
	Makita	UX01G	Weeding Attachment WA400MP	≤	2,8	1,5	ISO22867(ISO11806-1)		-	77	89	3	Uncertainty: K _{PA} /K _{WA}	ISO22868(ISO11806-1)	ng blade 220(725	
	Makita	UX01G	Weeding Attachment WA400MP		-	-	-		-	-	89,4	1,9	Guaranteed -91-dB	2000/14/EC	ng blade 220(725	
	Makita	VC001G(VC002G)	Cordless Vacuum Cleaner	≤	2,5	1,5	60335-2-69		≤	70	-	2,5	Vaccum-test-carpet	60335-2-69		
	Makita	VC003G(VC004G)	Cordless Vacuum Cleaner	≤	2,5	1,5	60335-2-69		≤	70	-	2,5	Vaccum-test-carpet	60335-2-69		
	Makita	VC005G	Cordless Vacuum Cleaner	≤	2,5	1,5	60335-2-69		≤	70	-	2,5	Vaccum-test-carpet	60335-2-69		
	Makita	VC006G(VC007G)	Cordless Vacuum Cleaner	≤	2,5	1,5	60335-2-69		≤	70	-	2,5	Vaccum-test-carpet	60335-2-69		
	Makita	VC008G(VC009G)	Cordless Backpack Vacuum Clea	≤	2,5	1,5	60335-2-69		≤	72	-	2,5	Vaccum-test-carpet	60335-2-69	p at Operators ea	
	Makita	VC010G	Cordless Upright Cleaner	≤	2,5	1,5	60335-2-69		≤	70	-	2,5	Vaccum-test-carpet	60335-2-69		
	Makita	VC011G(VC012G)	Cordless Backpack Vacuum Clea	≤	2,5	1,5	60335-2-69		≤	70	-	2,5	Vaccum-test-carpet	60335-2-69	Lp at Operators ea	
	Makita	VC014G(VC013G)	Cordless Vacuum Cleaner	≤	2,5	1,5	60335-2-69			75	-	2,5	Vaccum-test-carpet	60335-2-69	Vaccum mode	
	Makita	VC014G(VC013G)	Cordless Vacuum Cleaner	≤	2,5	1,5	60335-2-69			75	-	2,5	-	60335-2-69	Blower mode	
	Makita	VC1310L	Vacuum Cleaner		-	-	60335-2-69			72	-	2,5	-	60704-2-1		
	Makita	VC2201M	Vacuum Cleaner		-	-	60704-2-1			72,5	-	2,5	Vaccum-test-carpet	60704-2-1		
	Makita	VC2211M	Vacuum Cleaner		-	-	60704-2-1			72,5	-	2,5	Vaccum-test-carpet	60704-2-1		
	Makita	VC2510L	Vacuum Cleaner		-	-	60335-2-69			73	-	2,5	-	60704-2-1		
	Makita	VC3210L	Vacuum Cleaner		-	-	60335-2-69			73	-	2,5	-	60704-2-1		
	Makita	VC3211H	Vacuum Cleaner		-	-	60704-2-1			72,5	-	2,5	Vaccum-test-carpet	60704-2-1		
	Makita	VC3211M	Vacuum Cleaner		-	-	60704-2-1			72,5	-	2,5	Vaccum-test-carpet	60704-2-1		
	Makita	VC860D VC861D	Corded and Cordless Vacuum Cle	≤	2,5	1,5	60335-2-69			75	-	2,5	Vaccum-test-carpet	60704-2-1		
	Makita	VC862D	Cordless Vacuum Cleaner	≤	2,5	1,5	60335-2-69		≤	70	-	2,5	Vaccum-test-carpet	60335-2-69		
	Makita	VC863D	Cordless Vacuum Cleaner	≤	2,5	1,5	60335-2-69		≤	70	-	2,5	Vaccum-test-carpet	60335-2-69		
	Makita	VC864D	Cordless Vacuum Cleaner	≤	2,5	1,5	60335-2-69		≤	70	-	2,5	Vaccum-test-carpet	60335-2-69		
	Makita	VR001G VR003G VR004G	Cordless Concrete Vibrator		6,2	1,5	ENIEC62841-2-12		≤	70	-	3	load without flexible hose	ENIEC62841-2-12		
	Makita	VR250D	Cordless Concrete Vibrator	≤	2,5	1,5	60745-1			73	-	3	no-load	60745-1		
	Makita	VR251D	Cordless Concrete Vibrator	≤	2,5	1,5	60745-1			74	-	3	no-load	60745-1		
	Makita	VS001G	Cordless Vacuum Sweeper	≤	2,5	1,5	EN60335-2-72		-	≤	70	-	3	no-load	EN60335-2-72	p at Operators ea
	Makita	VS001G	Cordless Vacuum Sweeper	-	-	-	-		-	-	76 4	0 94	Guaranteed:77dB	2000/14/EC+2024/1208/EU		
	Makita	WR100D	Cordless Ratchet Wrench		2,1	1,5	EN62841-2-2		77	-	-	3	no-load	EN62841-2-2		
	Makita	WT001G	Shear Wrench		0,4	1,5	EN62841-2-2		82	-	90	3	no-load	EN62841-2-2		